Service Bulletin

HEAR THE POWER OF TECHNOLOGY.

Title:	**Replacement Part Number Updates**
Bulletin #:	QSC0001
Issue Date:	22 September 2010
Models Affected:	All
Bulletin Revision:	A
Production Range:	N/A

Description

Over time, QSC replacement parts often get updated or superseded, either with a different part number (as in the case of the original components used in the RMX and ISA series amplifiers, which were converted from the OEM supplier's numbers to QSC's 10-digit standard part number format), or an actual different part (this happens when a manufacturer discontinues a component, or an improved one becomes available, or when two or more otherwise interchangeable items are consolidated into a single part number).

The tables in this bulletin list the updated part numbers. Table 1 is for the RMX and ISA series amplifier parts, and Table 2 is for other parts that already used the QSC standard part number format. These guides will be of particular utility for technicians using older QSC service manuals that might now contain obsolete part numbers.

Notes on Table 1

In Table 1, the original part numbers in the first column may appear on older RMX and ISA schematics and service documentation but are now obsolete. They have been superseded by the current part numbers on the right. Please use the current part information when ordering from QSC Technical Services.

Table 1. RMX and ISA part updates

Original Part #	Description	New Part #	Description
061-076001-000	BLK KNOB	PL-000227-01	KNOB,BRACKET,C3-8,POLYSTYRENE,BLACK,
062-080202-000	TERMINAL COVER, CLEAR PLASTIC, 8 POSITION	PL-000613-GP	TERMINAL COVER,8 POS,,PLASTIC,CLR,
062-080203-000	TERMINAL COVER, CLEAR PLASTIC, 5 POSITION	PL-000614-GP	TERMINAL COVER,5 POS,,PLASTIC,CLR,
064-261904-0000	BACK COVER, I-82H, BLACK	PL-000304-01	BACK COVER, SHELL ONLY (NO HARDWARE),BLACK I-82H
090-308004-000	C3-8 HO WOOFER	SP-000163-GP	WOOFER,C3-8 HO,,,,
1402-7866-2	RMX850 CHASSIS	CH-000843-GP	CHASSIS,,,RMX850,
1402-7867-2	RMX1450 CHASSIS	CH-000844-GP	CHASSIS,,,RMX1450,
1402-7868-2	RMX2450 CHASSIS	CH-000131-GP	CHASSIS,RMX 2450
1402-7868-2	RMX2450 CHASSIS	CH-000195-GP	CHASSIS,BOTTOM,,RMX2450,
1403-6413-1	CHASSIS FAB ISA 1350	CH-000389-GP	CHASSIS FAB ISA 1350
1404-1113-1	CHASSIS BOTTOM RMX4050HD	CH-000221-GP	CHASSIS RMX 4050HD
1404-1201-0	COVER TOP 3550	CH-000230-GP	TOP COVER, RMX 4050HD / RMX 5050
1404-1201-1	TOP COVER RMX4050HD	CH-000230-GP	TOP COVER, RMX 4050HD / RMX 5050
145B-2340+1	CARTON,WITH CAP,FOR HPR 18SUB,TOP/BOTTOM,,,	PM-000268-GP	CAP,FOR HPR 18SUB,TOP/BOTTOM,,,
150F-101J-J-BD	CC 50V 100pF 5% 0805 1.2	CA-110005-GP	CC 50V 100PF 5% 0805 1.2
150F-104K-6-CF	CER2 1206 X7R 50V 100N	CA-410013-GP	CER 2 1206 10% 50V .1UF
150F-104K-J-BD	CC 50V 0.1uF 10% 0805	CA-410014-GP	0.1UF 10% 50V CER X7R 0805
150F-104M-J-BD	AVX .1UF 50V CER CAP 0805 X7R 5%	CA-410014-GP	0.1UF 10% 50V CER X7R 0805
150F-181K-J-BD	CC 50V 180P 10% 0805	CA-118000-GP	CC 50V 180PF 5% 0805
150F-221J-J-BD	CC 50V 220pF 5% 0805, 1.2X2.0	CA-122005-GP	CC 50V 220pF 5% 0805 1.2X2.0
150F-222K-6-CF	CC 50V 2200pF 10% 1206	CA-222007-GP	50V .0022UF 10% 1206
150F-222K-J-BD	CC 50V 2200PF 10% 0805, 1.2X2.0	CA-222017-GP	2200PF,10 PCNT,50V,CC,0805,
150F-223K-J-BD	CC 50V 2200PF 10% 0805, 1.2X2.0	CA-322007-GP	CC 50V .022UF 10% 0805
150F-332K-J-BD	CC 50V 3300pF 10% 0805 1	CA-233007-GP	.0033UF,10 PCNT,50V,CC,0805,
150F-470J-J-BD	CC 50V 47pF 5% 0805 1.2x	CA-047005-GP	CC 50V 47PF 5% 0805
150F-471J-5-OF	CC 50V 470pF 5% RL	CA-147006-GP	470PF 5% 50V CER NPO
150F-474M-5-II	CC 50V 0.47UF 20% RL 5X5	CA-447013-GP	.47UF,20 PCNT,50V,CC,RL 5X5,
150F-474M-5-LL	CC 50V 0.47UF 20% RL 5X5, MONO	CA-447013-GP	.47UF,20 PCNT,50V,CC,RL 5X5,
150F-560K-J-BD	CC 50V 56pF 10% 0805	CA-056001-GP	CC 50V 56PF 10% 0805
150F-562J-J-BD	CC 50V 5600pF 5% 0805 1.	CA-256002-GP	0.0056UF 5% 50V CER X7R 0805

Continued on next page ➜

Table 1, continued. RMX and ISA part updates

Original Part #	Description	New Part #	Description
150T-222M-5-SK	CC 400V 2200P 20% RL Y5V	CA-222011-GP	.0022UF 20% 400V CER RL
150U-150J-J-BD	CC 200V 15P 5% 0805 COG	CA-015004-GP	15PF 5% 200V CERAMIC X7R 0805
153F-154J-5-NLM	CM 50V 0.15UF 5%	CA-415004-GP	0.15U,5%,50V,CM,,RBT,7.5X
153F-223J-5-LQ	CM 50V 0.022UF 5%F	CA-322006-GP	CM 50V .022UF 5% RL
153F-332J-5-KW	CM 50V 3300pF 5%	CA-233004-GP	CM 50V .0033UF 5% RL
153H-102J-5-IQ	CM 100V 0.001UF 5%	CA-210012-GP	CM 100V .001UF 5% RL 5X
153H-104J-5-XX	CM 100V 0.1U 5% RL, 12.5X12.5MM	CA-410031-GP	0.1U,5 PCNT,100V,CM,12.5 X 12.5,
153H-154J-5-XX	CM 100V 0.15UF 5% RL	CA-415005-GP	0.15UF 5% 100V MYLAR
153H-474J-5-XX	CM 100V 0.47U 5% RL 12.5x 12.5MM	CA-447015-GP	.47UF,5 PCNT,100V,CERAMIC,RL 12.5 X 12.5MM,
153R-103J-5-YRM	CM 250V 0.01 UF 5% RL 13X9.5 META	CA-310011-GP	.01UF 5% 250V METALIZED POLY
153R-104J-5-YRM	CM 250V 0.1u 5% RL	CA-410018-GP	CM 250V .1UF 5% RL
153R-152J-5-XQ	CM 250V 0.0015UF 5%	CA-215004-GP	CM 250V .0015UF 5% RL
153R-222J-5-XQM	CM 250V 0.0022UF 5% RL	CA-222012-GP	0.0022UF,5 PCNT,250V,RADIAL,,
153R-224K-5-Y1	CM 250V 0.22uF 10%	CA-422005-GP	CM 250V .22UF 10% RL
153R-683J-5-WWM	CM 250V 0.068u 5%	CA-368004-GP	0.068UF 5% 250V FILM DIPPED
157D-106M-5-GIF4	CE 16V 10UF 20%	CA-610010-GP	10UF 20% 16V ELECTOLYTIC R3S
157D-107M-5-OUN	CE 16V 100UF 20%	CA-710010-GP	CE 16NP 100UF 20% RL 8X11
157D-476M-5-LUN	CE 16V 47U 20%	CA-647006-GP	CE 16NP 47UF 20% RL
157E-106M-5-GMK	CE 25V 10UF 20% RL 4X7	CA-610014-GP	10UF 20% 250V ELECTROLYTIC
157E-107M-5-KW	CE 25V 100uF 20%	CA-710009-GP	CE 25V 100UF 20% RL
157E-226M-5-IUN	CE 25V 22uF 20%	CA-622007-GP	CE 25NP 22UF 20% RL 5X11
157E-227M-5-PU	CE 25V 220uF 20%	CA-722006-GP	CE 25V 220UF 20% RL
157E-228M-5-X9	CE 25V 2200uF 20% RL	CA-822001-GP	2200UF 20% 25V ELECTRO RADIAL
157F-106M-5-LUN	CE 50V 10UF 20%	CA-610020-GP	CE 50V 10UF 20% RLT 5 X 11
157F-106M-K-IUI	CE 50V 10UF 20% RLT 5X11, SHOE	CA-610020-GP	CE 50V 10UF 20% RLT 5 X 11
157F-107M-K-OVI	CE 50V 100U 20%RLT, 8X11.5,SHOE	CA-710012-GP	CE 25V 100UF 20% RLT 8X11.5
157F-159M-5	CE 50V 15000UF 20% RL	CA-915001-GP	15000UF,20 PCNT,50V,ELECTROLYTIC,,
157F-476M-5-LU	CE 50V 47UF 20%	CA-647005-GP	CE 50V 47UF 20% RL
157Q-106M-5-IU	CE 35V 10uF 20% RL 5x11	CA-610009-GP	CE 35V 10UF 20% RL 5 X 11
157Q-108M-5-X9E	CE 35V, 1000UF, 20%	CA-810006-GP	1000UF 35V 20% ELECTROLYTIC
157Q-476M-5-LUA	CE 35V 47U 20% RL 6.5X11	CA-647008-GP	47UF 20% 35V ELECTROLYTIC
157R-475M-5-OV	CE 250V 4.7u 20%	CA-547008-GP	4.7UF 20% 250V ELECTRO RAD
15CG-270J-J-BD	CTC 0/30 27P 5% 0805	CA-027004-GP	27PF 5% 50V COG 0805
1660-0510-0	SHRINKAGE TUBE ID=12, UL/CSA	WC-000329-GP	PVC TUBING,HEAT SHRINK,ID=12 UL/CSA
1660-0630-0	SHRINKAGE TUBE ID=14MM	WC-000189-GP	PVC TUBING,HEAT SHRINK,ID=14MM
1660-0880-0	SHRINKAGE TUBE ID=6MM UL	WC-000423-GP	PVC TUBING,HEAT SHRINK,ID=6MM X 1 IN. LENGTH (3PCS)UL,,,,,
1660-0890-0	SHRINKAGE TUBE ID=1MM UL	WC-000184-GP	HEAT SHRINK TUBING, 12in. x 1MM
1660-1160-0	SHRINKAGE TUBE ID=18MM UL/CSA 125C	WC-000219-GP	PVC TUBING,HEAT SHRINK, 12in. x 18MM
1681-2000-A	UL1007 AWG#22 BLACK	WC-000224-GP	UL 1007 AWG #22 BLK
1681-8010-C	UL1015 AWG# 14 BROWN	WC-000199-GP	UL 1015 AWG#14 BROWN
1681-8060-C	UL1015 AWG# 14 BLUE	WC-000382-GP	WIRE,UL1015,14 AWG, BLUE,,,,
1804-1040-0	SPRING COIL 2uH	XF-000190-GP	SPRING COIL 2UH (14GA WIRE)
1806-2421+0	TOROIDAL TRANSFORMER, 120/230V	XF-000193-GP	TRANSFORMER (1806-2421+0),120/230v, ISA280/300T
1806-2422+0	TOROIDAL TRANSFORMER	XF-000189-GP	TRANSFORMER,(1806-2422+0),120/240v, ISA450/500T
1806-2440-0	RMX1850HD TRANSFORMER	XF-000105-GP	TRANSFORMER (1806-2440-0),,,,,RMX1850,,
1806-2505-0	RMX850 TRANSFORMER (120V / 230V)	XF-000117-GP	TRANSFORMER (1806-2505-0),,,,,RMX850,,
1806-2506-0	RMX1450 TRANSFORMER (120V / 230V)	XF-000116-GP	POWER TRANSFORMER,,,,100V,RMX1450,,
1806-2507-0	RMX2450 TRANSFORMER (120V / 230V)	XF-000115-GP	TRANSFORMER (1806-2507+0), 120/230V,,,,,RMX 2450,,
1806-3542+1	OBS-TRANSFORMER,I/P: 100/120/240,,,,,,	XF-000192-GP	TRANSFORMER,(1806-3542+1),120/240v, ISA800T/750
1806-3543-1	LINE TRANSFORMER TOROIDAL	XF-000191-GP	TRANSFORMER,(1806-3543-1),LINE XFMR ISA 300T
1806-3544-1	LINE TRANSFORMER TOROIDAL	XF-000225-GP	TRANSFORMER,(1806-3544+1),LINE XFMR ISA 500T
1806-3545-2	LINE TRANSFORMER TOROIDAL	XF-000226-GP	TRANSFORMER,(1806-3662+0)LINE XFMR ISA 800T
1806-3567+1	TRANSFORMER,RMX4050/ISA1350,50/60HZ,100/120/240,TOROID,CH2 RT	XF-000201-GP	TRANSFORMER,(1806-3567+1),RMX4050/ISA1350,50/60HZ,100/120/240,TOROID,CH2 RT
1806-3610-0	INDUCTOR 1.57MH 30% DUAL	XF-000224-GP	INDUCTOR 1.57MH 30%
1806-3610-1	INDUCTOR 1.57MH 30% DUAL	XF-000224-GP	INDUCTOR 1.57MH 30%
1806-3621+0	TRANSFORMER,RMX4050/ISA1350,50/60HZ,100/120/240,TOROID,CH1 LEFTRT	XF-000229-GP	TRANSFORMER,(1806-3621+0),RMX4050/ISA1350,50/60HZ,100/120/240,TOROID,CH1 LEFTRT

Continued on next page ➜

Table 1, continued. RMX and ISA part updates

Original Part #	Description	New Part #	Description
1806-3635+0	XFMR T/P=100/120/240	XF-000232-GP	TRANSFORMER,(1806-3635+0),120/230V,50/60HZ (RMX4050 RIGHT), CH 2
1806-3636+0	XFMR I/P=100/120/240	XF-000233-GP	TRANSFORMER,(1806-3636+0),120/230,PWR 50/60HZ (RMX4050 LEFT), CH 1
1806-3645-0	XFMR I/P=100/120/240	XF-000228-GP	TRANSFORMER (1806-3645-0),PWR,50/60HZ,TOROID,CH1 LT
1806-3646-0	XFMR I/P=100/120/240	XF-000227-GP	TRANSFORMER (1806-3646-0),PWR,50/60HZ,TOROID,CH2 RT
1806-3660-0	ISA 300TI OUTPUT TRANSFORMER	XF-000268-GP	TRANSFORMER (1806-3660+0),LINE TRANSFORMER, ISA 300TI
1806-3871+0	POWER TRANSFORMER,(1806-3871+2),120V,,,,HPR SERIES,,	XF-000293-GP	POWER TRANSFORMER,(1806-3871+2),120V,,,,HPR SERIES,,
1806-3871+2	POWER TRANSFORMER,(1806-3871+2),120V,,,,HPR SERIES,,	XF-000293-GP	POWER TRANSFORMER,(1806-3871+2),120V,,,,HPR SERIES,,
1806-3871-0	POWER TRANSFORMER,(1806-3871+2),120V,,,,HPR SERIES,,	XF-000293-GP	POWER TRANSFORMER,(1806-3871+2),120V,,,,HPR SERIES,,
1806-3982+0	TRANSFORMER,,,,120V,RMX850,,	XF-000315-GP	TRANSFORMER (1806-3982+0000),,,,120V,RMX850,,
1806-3983+0	TRANSFORMER,,,,240V,RMX850,,	XF-000314-GP	TRANSFORMER (1806-3983+0000),,,,240V,RMX850,,
1806-3984+0000	TRANSFORMER,,,,120V,RMX1450,,	XF-000317-GP	TRANSFORMER (1806-3984+0000),,,,120V,RMX1450,,
1806-3985+0000	TRANSFORMER,,,,240V,RMX1450,,	XF-000316-GP	TRANSFORMER,(1806-3985+0000),,,,240V,RMX1450,,
1806-3986+0	TRANSFORMER,,,,120V,RMX2450,,	XF-000319-GP	TRANSFORMER (1806-3986+0000),,,,120V,RMX2450,,
1806-3987+0	TRANSFORMER,,,,240V,RMX2450,,	XF-000318-GP	TRANSFORMER,,,,(1806-3987+0000),240V,RMX2450,,
1806-3988+0000	TRANSFORMER,,,,120V,RMX1850HD,,	XF-000321-GP	TRANSFORMER (1806-3988+0000),,,,120V,RMX1850HD,,
1806-3989+0000	TRANSFORMER,,,,240V,RMX1850HD,,	XF-000320-GP	TRANSFORMER (1806-3989+0000),,,,240V,RMX1850HD,,
1806-3994+0000	TRANSFORMER,240V,ISA450/500Ti,,	XF-000325-GP	TRANSFORMER,(1806-3994+0000),240V,ISA450/500Ti,,
1806-3999+0000	TRANSFORMER,LEFT, CHANNEL 1,,,240V,RMX4050HD/ ISA1350,,	XF-000331-GP	TRANSFORMER,(1806-3999+0000),LEFT, CHANNEL 1,,,240V,RMX4050HD/ISA1350,,
1806-4001+0000	TRANSFORMER,RIGHT, CHANNEL 2,,,240V,RMX4050HD/ ISA1350,,	XF-000332-GP	TRANSFORMER,(1806-4001+0000),RIGHT, CHANNEL 2,,,240V,RMX4050HD/ISA1350,,
1806-4002+0000	TRANSFORMER,LEFT, CHANNEL 1,,,120V,RMX5050,,	XF-000334-GP	TRANSFORMER,LEFT, CHANNEL 1,,,120V,RMX5050,,
1806-4003+0000	TRANSFORMER,RIGHT, CHANNEL 2,,,120V,RMX5050,,	XF-000336-GP	TRANSFORMER,RIGHT, CHANNEL 2,,,120V,RMX5050,,
1806-4004+0000	TRANSFORMER,LEFT, CHANNEL 1,,,240V,RMX5050,,	XF-000333-GP	TRANSFORMER,(1806-4004+0000),LEFT, CHANNEL 1,,,240V,RMX5050,,
1806-4005+0000	TRANSFORMER,RIGHT, CHANNEL 2,,,240V,RMX5050,,	XF-000335-GP	TRANSFORMER,(1806-4005+0000),RIGHT, CHANNEL 2,,,240V,RMX5050,,
2101-1231-0	SPADE TERMINAL 6.3X0.8	CO-000221-GP	Z-TAB ISA
2101-1373-0	CONN.PLUG 3-PIN EURO, GREEN	CO-000228-GP	EURO 3 PIN CONNECTOR, GREEN
2101-1386-0	WAFER 6P P=6.7	CO-000281-GP	HDR 6.3MM CNTR 6P(2X3)MALE
2101-1388-0	SOCKET 14P DUAL ROW IEC	CO-000282-GP	HDR,2.5MM CNTR 14P(2X7)MALE,LK
2101-1395-0	SOCKET 30PIN DUA/ROW IEC	CO-000278-GP	HDR .1 CNTR 30P(2X15)MALE LOCK
2101-1991-0	8 PIN IC SOCKET DIP	CO-000222-GP	8-PIN IC SOCKET
2101-2081-0	26 PIN DUAL ROW IEC SOCKET	CO-000223-GP	26-PIN DUAL ROW IEC
2101-9400-0	JM2422-3M WAFER	CO-000279-GP	JM2422-3M WAFER
2102-021S-004	2P ST.WAFER	CO-000213-GP	CONN,STRAIGHT WAFER,2 PIN,,
2102-031R-004	WAFER 3P P2.5 RIGHT ANGLE	CO-000209-GP	HEADER 3-PIN RIGHT ANGLE
2102-031S-004	WAFER 3PIN P2.5 STRAIGHT	CO-000214-GP	CONN 3 PIN STRAIGHT WAFER
2102-041R-004	WAFER 4P P2.5 RIGHT ANGLE	CO-000210-GP	HEADER 4-PIN RIGHT ANGLE
2102-041S-004	WAFER 4P P2.5 STRAIGHT	CO-000215-GP	CONN 4 PIN STRAIGHT WAFER
2102-061R-004	WAFER 6P P2.5 RIGHT ANGLE	CO-000205-GP	HEADER 6-PIN RT ANGLE
2102-061S-004	WAFER 6P STRAIGHT	CO-000224-GP	CONN 6 PIN ST. WAFER
2102-071S-004	WF T8 DE 7PIN COULOMB	CO-000280-GP	HDR 2.5MM CNTR 7P(1X7)MALE
2102-081S-004	WAFER 8P P2.5 STRAIGHT	CO-000216-GP	CONN 8 PIN STRAIGHT WAFER
2102-130S-003	WAFER 13P P2.0 STRAIGHT	CO-000217-GP	CONNECTOR,13 PIN STRAIGHT WAFER,,,2.0 PITCH
2113-1144-0	AC INLET	CO-000211-GP	AC INLET 250V 15A
2113-1335-0	5 POLE SPEAKER TERMINAL	CO-000234-GP	5 POLE INPUT TERMINAL BLOCK
2113-1336-1	SPEAKON NEUTRIK 4 WIRE NL4MD-V	CO-000236-GP	SPEAKON NEUTRIK 4 WIRE
2113-1337-1	XLR FEMALE CONN. NC3FAV1-0	CO-000204-GP	CONN XLR F VERT PLASTIC
2113-1338-0	PLATE ASSY, RMX	PA-000043-00	PLATE ASSY,PLX/RMX,OUTPUT,,
2113-1652-0	PHONE JACK 06.4 JY-6351-02-030	CO-000235-GP	PHONE JACK 06.4
2113-1713-0	6 POLE SPEAKER TERMINAL	CO-000218-GP	6 POLE SPEAKER TERMINAL
2113-1720-0	3 PIN INPUT JACK	CO-000219-GP	3 PIN INPUT JACK
2113-1724-1	CONN.HD-15 15-WAY D-TYPE, RIGH	CO-000220-GP	CONN HD15
2150-6741-0	PC INLAY (WARNING LABEL)	LB-000354-GP	LABEL,TOP COVER, WARNING
2150-6742-0	PC INLAY (WARNING LABEL),QSC	LB-000438-GP	LABEL,WARNING,RAIN & MOISTURE
2150-6791-0	PVC SHEET 82X35X0.5	PL-000181-GP	PVC SHEET
2444-1001-1	CONTROL KNOB	PL-000147-GP	KNOB RMX PLASTIC BLACK

Continued on next page ➜

Table 1, continued. RMX and ISA part updates

Original Part #	Description	New Part #	Description
2445-1501-0	CONTROL KNOB	CH-000169-GP	OBS-VR KNOB ISA SERIES
2600-3004-0803	METAL WASHER M3X0.4X8 BZ	NW-030001-GP	WASHER M3.0 X 0.4 X 8 BZ
2600-7005-1102	METAL WASHER M7x0.5x11mm	NW-070001-GP	WASHER M7 X .5 X 11MM METAL
2600-9005-1402	WASHER M9X0.5	NW-100001-GP	FLAT WASHER, M9 X .5 X 14 THK
2600-9505-1402	METAL WASHER M9.5X0.5X14	NW-100001-GP	FLAT WASHER, M9 X .5 X 14 THK
2606-3005-0642	I/T WASHER M3X0.5X6.4 WZ	NW-030002-GP	I/T WASHER M3 X 0.5 X 6.4 WZ
2606-4004-0800	I/T WASHER M4X0.4X8 YZ	NW-040003-GP	I/T WASHER M4X0.4X8,YZ
2607-3007-0550	SPRING WASHER	NW-000002-GP	SPRING WASHER,3M,,,,,,,,
2607-3009-0553	SPRING WASHER M3X0.9X5.5 MM BZ	NW-030000-GP	SPRING WASHER M3 X 0.9 X 5.5
2607-4010-0700	SPRING WASHER M4X7 YELLOW ZINC	NW-040002-GP	SPRING WASHER M4 X 7
2640-4030-0704	NUT HEX M4	NW-040006-GP	HEX NUT M4 X 0.7 X 7MM
2640-7020-1000	NUT M7x2x10mm YZ	NW-070000-GP	SRV-NUT M7 X 2 X 10MM YZ
2842-3367-0	METAL WASHER ID=3.3 OD=6.7	NW-000004-GP	METAL WASHER,,,,,,,,,
2904-3005-3000	SCREW BH M3X 5 MM BZ CRO	SC-030016-GP	SCREW M3 X 5MM BLK
2904-3005-4000	SCREW BH M3X 5 MM NI CRO	SC-000212-GP	SCR,,BH,,,,,M3 X 5MM,,NI CRO,,,
2904-3006-3000	SCREW M3X6 BINDING (BLK)	SC-030008-GP	SCREW M3X6 BLK TAP
2904-3008-3000	SCREW M3X8 (BLK)	SC-030004-GP	M3 X 8 BLK MACHINE
2904-3008-4000	M3X8MM(NICKEL)	SC-030011-GP	M3 X 8 MM NICKEL
2904-3012-3000	M.SCREW M3X12 B/H BLACK ZINC	SC-030010-GP	SCREW M3X0.5X12MM,B/H,BLK ZN
2904-3014-3000	SCREW BH M3X 14 MM BZ CR OSS	SC-030006-GP	M3 X 14MM BZ CR BH
2904-4010-3000	SCREW M4X10 (BLK)	SC-040006-GP	SCREW, M4X10MM, BLK
2904-4035-3000	SCREW M4X35mm BH BZ	SC-040005-GP	SCREW M4 X 35MM BH BZ
2908-3012-3000	SCREW M3X12, HEX HEAD BLACK ZINC	SC-000206-GP	SCREW,,HEX HEAD,,,,,M3,12 L,,BLACK,ZINC,
2951-3010-3000	SCREW B-TITE FLAT-CS M3X 10 MM BZ CROSS	SC-030002-GP	M3 B-TITE FLAT-CS
2954-3006-3000	3X6MM B-TITE (BLK.ZN)	SC-000128-GP	OBS-SCREW M3X6 BLACK MACHINE
2954-3006-3000	3X6MM B-TITE (BLK.ZN)	SC-030007-GP	M3 X 6MM B-TITE BLK ZN
2954-3008-3000	T3X8MM SELF TAPPING	SC-000081-GP	T3X8MM,SELF TAPPING,,,,
2954-3010-3000	B-TITE 3X10MM (BLK.ZN)	SC-030001-GP	BH M3 X 10MM BZ CRD,B-TITE
2954-3012-3000	3X12MM B-TITE (BLK.ZN)	SC-030005-GP	M3 X 12MM (BLK/ZINC)
2954-4010-3000	SCREW TAP-C2 B.H M4X 10 M M BZ CROSS	SC-040001-GP	SCREW M4-18 X 10MM, BLK ZN
3000-8889-0	GROUND LABEL	LB-000355-GP	LABEL, GROUND
3000-9360-0	LABEL CARTON RMX4050HD	RD-000082-00	LABEL,SHIPPING CARTON,GPE AMPLIFIERS
3000-9361-0	LABEL CARTON RMX4050HD	RD-000082-00	LABEL,SHIPPING CARTON,GPE AMPLIFIERS
3000-9394-1	LABEL SERIAL NO. &	RD-000144-00	LABEL,SERIAL NUMBER,AMPLIFIERS,OEM
3000-9395-2	LABEL SERIAL NO. & RATIN	RD-000144-00	LABEL,SERIAL NUMBER,AMPLIFIERS,OEM
3000-9396-0	UL LABEL FOR RMX4050HD	LB-000410-GP	LABEL "UL LISTED"
3000-9436-0	LABEL CARTON RMX5050HD	RD-000082-00	LABEL,SHIPPING CARTON,GPE AMPLIFIERS
3000-9437-1	LABEL CARTON RMX5050 FOR	RD-000082-00	LABEL,SHIPPING CARTON,GPE AMPLIFIERS
3000-9438-0	LABEL SERIAL NO.&RATING	RD-000144-00	LABEL,SERIAL NUMBER,AMPLIFIERS,OEM
3000-9439-0	LABEL SERIAL NO. &	RD-000144-00	LABEL,SERIAL NUMBER,AMPLIFIERS,OEM
3000-9916-0	LABEL SERIAL NO. & RATING, ISA 13	RD-000144-00	LABEL,SERIAL NUMBER,AMPLIFIERS,OEM
3000-9917-0	LABEL SERIAL NO. & RATING ISA	RD-000144-00	LABEL,SERIAL NUMBER,AMPLIFIERS,OEM
3005-0491-0	SERIAL NO.& RATING LABEL 2000 (U)	LB-000382-GP	LABEL S/N,,,,
3005-0493-1	CE LABEL 230V	LB-000371-GP	LABEL,CE,,,
3005-0495-0	SERIAL NO. LABEL 800(U)	RD-000082-00	LABEL,SHIPPING CARTON,GPE AMPLIFIERS
3005-0502-0	UL LABEL FOR QZ MODEL	LB-000356-GP	OBS-LABEL, UL
3030-1238-0	WARRANTY CARD	TD-000096-GP	WARRANTY CARD
3030-1238-1	WARRANTY CARD QSC	TD-000900-AX	WARRANTY CARD,GENERIC,20# OR EQUIVALENT COPY PAPER
3100-6081-0	INSULATION SHEET IC	PL-000257-GP	SRV-INSULATION TO-220 46X19MM X.23
3100-6121-0	INSULATION SHEET IC	PL-000246-GP	SRV-INSUL,XISTOR,11.6X19X.23,THERM
3130-2430-0	IC-NE5532 OPER. AMP PHIL IPS	IC-000211-GP	IC NE5532 OP AMP
3130-9240-0	IC LM311M VOLTAGE	IC-000214-GP	LM311M VOLTAGE
3130-9260-0	IC LM13600M	IC-000212-GP	IC LM13700M
3130-9270-0	IC 4N29	IC-000213-GP	IC 4N29
3132-1981-0	IC NE2517D	IC-000077-GP	IC LM13700M,,,SMT,
3700-1622-R	LED 04MM RED	QD-000360-GP	LED,04MM, RED,,,,,
3700-1623-G	LED 04MM GREEN	QD-000361-GP	LED,04MM, GREEN,,,,,
3700-1624-R	LED 4.7MM RED AC W/STAND	QD-000255-GP	LED RED 4.7MM AC W/RT ANG&HLDR

Continued on next page ➜

Table 1, continued. RMX and ISA part updates

Original Part #	Description	New Part #	Description
3700-4529-R	LED 04MM RED W/STAND	QD-000197-GP	LED 4.7MM RED W/STAND
3700-4530-Y	LED 04MM YELLOW W/STAND	QD-000199-GP	LED 4.7MM W/STAND YELLOW
3700-4531-G	LED 04MM GREEN W/STAND	QD-000198-GP	LED 4.7MM GRN W/STAND
4131-9131-0	FUSE HOLDER 6.5MM PITCH, RECT	HW-000151-GP	FUSE HOLDER,6.5MM PITCH, RECT,,,,
4131-9321-0	TERMINAL WRAP	CO-000212-GP	TERMINAL WRAP
4132-1671-0	TRANSISTOR CLAMP	CH-000172-GP	CLAMP TRANSISTOR
4134-8421-0	BRASS STUD M3 L=18mm	SC-030009-GP	BRASS STUD M3 18MM LG
4134-8432-0	CORNER BRACKET L-SHAPE	CH-000198-GP	RACK-MOUNT BRACKET
4134-8851-0	FUSE HOLDER (DIA.6.3MM FUSE)	HW-000020-GP	FUSE HOLDER 6.3MM
4134-9091-1	BRASS STUD M3X24.5	HW-300001-GP	STANDOFF,5.5 HEX,M3X24.5,BRASS
4134-9101-0	METAL WIND GUIDE	CH-000194-GP	FAN SHROUD RMX
4135-0182-0	TOP COVER 1350	CH-000390-GP	TOP COVER ISA 1350
4135-0191-1	PCB HOLDER 280 SECC	CH-000165-GP	PCB HOLDER ISA GPE
4135-0201-0	PCB BRACKET 280 SECC	CH-000171-GP	BRACKET, RT ANGLE HD15
4135-0282-0	FAN GUARD FOR 120mm FAN	MS-000190-GP	FAN GUARD WIRE 120MM BLACK
4135-0451-0	VR BRACKRT 280C	CH-000168-GP	VR BRACKET ISA
4135-0471-0	PCB BRACKET3 (280)	CH-000170-GP	BRACKET AC PCB MTG
4135-0811-0	NUT M4 W/EXTERNAL TOOTH	NW-040001-GP	NUT KEPS M4
4135-0942-0	TRANSFORMER STEEL COVER	CH-000173-GP	COVER,XFMR,STEEL,LARGE
4135-1241-0	PROTECT COVER	CH-000167-GP	OBS-COVER ISA 450
4135-2141-0	CLAMP IC 6FINGERS	CH-000247-GP	CLAMP TRANSISTER 6 FINGER
4135-2151-0	CLAMP IC 4FINGERS	CH-000248-GP	CLAMP TRANSISTER 4 FINGER
4135-2161-0	HOLDER PCB 3550	CH-000231-GP	PCB HOLDER RMX 4050HD
4135-2161-1	HOLDER PCB RMX5050	CH-000366-GP	PCB HOLDER,,,RMX 5050,
4135-2731-0	NTC HOLDER FOR RMX4050HD	CH-000308-GP	NTC HOLDER
4135-2931-0	REAR RACK EAR RMX4050HD	CH-000301-GP	REAR RACK EAR, 3IN. UNIVERSAL
4135-2971-0	SCREW #8-32 X3/8"	SC-000207-GP	SCREW,#8-32 X 3/8",,,,,,,,,,
4135-2981-0	EXTERNAL 700 LOCKWASHER #8	NW-080006-GP	EXTERNAL LOCKWASHER,#8,700,,
4135-3121-0	SCREW 4X10 BLACK ZN TAPP	SC-000208-GP	SCREW,4X10 BLACK ZN TAPP,,,,,,,,,,
4135-3891-0	X'FER MOUNTING ASSY M8	SC-000018-GP	BOLT,PHILLIPS,,,,
4151-9931-0	INSULATION BUSHING	PL-000162-GP	INSULATION BUSHING
4152-0671-0	SILICON RUBBER TUBES.	PL-000578-GP	SILICON RUBBER TUBES,,,,,
4152-3584-0	NYLON SPACER 03X9	HW-000025-GP	SPACER, LED
4152-5151-0	INSULATION SHEET IC13X1	PL-000154-GP	INSULATION SHEET IC ISA
4152-5541-0	NYLON WASHER ID=3.2MM THK=0.8MM	NW-032000-GP	WASHER NYLON ID 3.2MM
4154-0241-0	RUBBER FOOT QZ MODEL	PL-000156-GP	RUBBER FEET
4154-0361-0	FAN GUIDE	MS-000137-GP	FAN GUARD WIRE 76MM RMX
4154-0461-0	RUBBER PAD 20X20 THK=3mm	PL-000171-GP	RUBBER PAD 20X20
4154-0671-0	SILICON RUBBER 22X19mm	PL-000155-GP	INSULATION SILICON FOR TO-220
4154-0691-0	POINTER ADAPTOR	PL-000170-GP	POINTER ADAPTER
4154-1511-0	LED HOLDER	PL-000150-GP	LED HOLDER
4154-3431-0	TRANSFORMER RUBBER PAD	PL-000157-GP	XFMR RUBBER PAD BLACK
4154-3432-0	TRANSFORMER RUBBER PAD	PL-000575-GP	TRANSFORMER RUBBER PAD,,,,,
4154-5091-0	PLATE PCB PROTECT PP	PL-000248-GP	DISPLAY PCB SHEILD
4154-5551-0	SHELTER FROM SEEN FOR	PL-000249-GP	VISUAL SHEILD,RMX-3RU
4154-5731-0	RIBBON SLEEVE RMX4050HD	PL-000253-GP	OBS-SLEEVE,RIBBON,50X120X.4MM,BLK
4154-6401-0	PVC PAD FOR RMX5050	PL-000579-GP	PVC PAD,RMX 5050,,,,
4154-7031-0	DIS PCB PROTECT SHEET PP	PL-000324-GP	DISPLAY PCB SHIELD,,,,,
4154-7041-0	CAP PROTECT SHEET PC	PL-000326-GP	MAIN PCB CAP SHEILD,,,,,
4157-0201-1	TRANSFORMER PAD SAFT	PL-000259-GP	SRV-PAD,XFMR,BLK,1/8 THICK
4157-0221-0	TRANSFORMER PAD EPDM 80A	PL-000268-GP	SRV-PAD, XFMR, BLK, 1/16" THICK
4157-0471-0	INSULATION SHEET IC	PL-000328-GP	SRV-INSULATOR,TO-220,4-POS,,,
4301-4193-1	USER'S MANUAL RMX4050HD	TD-000109-00	OWNERS MANUAL, RMX4050HD/RMX5050
4301-7044-0	USER MANUAL RMX4050	TD-000109-00	OWNERS MANUAL, RMX4050HD/RMX5050
4301-7095-2	USER MANUAL ISA	TD-000136-00	OWNERS MANUAL, ISATI/ISA SERIES(NEW)
4701-202J-C	RCF 1/8W 2K 5% ATS	RE-120003-GP	RCF 1/8W 2K 5% ATS
4701-682J-C	RCF 1/8W 6.8K 5% ATS	RE-168002-GP	RCF 1/8W 6.8K 5% ATS
4715-100J-2	RMF 1/4W 10R 5% AT	RE-001005-GP	RMF 1/4W 10 OHM 5%

Continued on next page ➜

Table 1, continued. RMX and ISA part updates

Original Part #	Description	New Part #	Description
4715-101J-2	RMF 1/4W 100R 5% AT	RE-010008-GP	RMF 1/4W 100 OHM 5%
4715-1691-2	RMF 1/4W 1.69K 1% AT	RE-116902-GP	1.69K 1% 1/4W AT
4715-184A-2	RMF 1/4W 180K 1% AT	RE-318001-GP	180K 1% 1/4W METAL FILM
4717-103A-2	RMF 1/2W 10K 1% AT	RE-210010-GP	RMF 1/2W 10.0K 1% AT
4717-1332-2	RMF 1/2W 13.3K 1% AT	RE-213304-GP	RMF 1/2W 13.3K 1% AT
4717-2322-2	RMF 1/2W 23.2K 1% AT	RE-223202-GP	RMF 1/2W 23.2K 1% AT
4717-754A-1	RMF 1/2W 750K 1% AL	RE-375003-GP	750K 1% 1/2W METAL FILM
4717-9091-2	RMF 1/2W 9.09K 1% AT	RE-190903-GP	RMF 1/2W 9.09K 1% AT
4718-120J-2-P	RMF 1W 12R 5% AT FP	RE-001204-GP	12 5% 1W METAL FILM
4718-123J-2-X	RMF 1W 12K 5% AT METAL OXIDE	RE-212002-GP	RMF 1W 12K 5% AT METAL
4718-130J-2-X	RMF 1W 13R 5% AT METAL	RE-001300-GP	RMF 1W 13 OHM 5% AT MET OX
4718-153J-2-X	RMF 1W 15K 5% AT METAL OXIDE	RE-215007-GP	RMF 1W 15K 5% METAL
4718-220J-2-P	RMF 1W 22R 5% AT FP	RE-002202-GP	RMF 1W 22 5% AT FP
4718-223J-2-X	RMF 1W 22K 5% AT	RE-222009-GP	22K,5 PCNT,1W,RMF,,
4718-2R7J-2-X	RMF 1W 2.7R 5% AT METAL	RE-.27002-GP	2.7 OHM,5 PCNT,1W,METAL FILM,,
4718-393J-2-X	RMF 1W 39K 5% AT METAL	RE-239002-GP	39K 5% 1W METAL FILM
4718-3R0J-2-X	RMF 1W 3.0R 5% AT METAL	RE-.30005-GP	3.0 OHM,5 PCNT,1W,AT METAL,RMF,
4718-3R3J-1-X	RMF 1W, 3.3R, 5% AL	RE-.33001-GP	RMF 1W 3.3 OHM 5%
4718-6R8J-1-X	RMF 1W 6.8R 5% AL METALOX	RE-.68001-GP	RMF 1W 6.8 OHM 5%
4719-102J-1-X	RMF 2W 1K 5% AL	RE-110018-GP	1K,5 PCNT,2W,AL,,
4719-121J-1-X	RMF 2W 120R 5% AL METAL OXIDE	RE-012004-GP	RMF 2W 120 OHM 5%
4719-150J-1-X	RMF 2W 15R 5% AL METALOX	RE-001508-GP	15 OHM,5 PCNT,2W,AL METALOX,,
4719-153J-1-X	RMF 2W 15K 5% AL METALOX	RE-215006-GP	RMF 2W 15K 5% AL METAL
4719-1R5J-1-X	RMF 2W 1R5 5% AL METAL OXIDE	RE-.15003-GP	1.5 OHM 5% 2W THK FLM
4719-202J-1-X	RMF 2W 2K 5% AL METALOXI	RE-120010-GP	2K,5 PCNT,2W,RMF AL METALOXI,,
4719-302J-1-X	RMF 2W 3K 5% AL METALOXI	RE-130007-GP	3K,5 PCNT,2W,RMF AL METALOXI,,
4719-333J-2-X	RMF 2W 33K 5% AT METAL	RE-233002-GP	RMF 2W 33K 5% METAL
4719-5R6J-1-X	OBS-RMF 2W 5.6R 5% AL METAL OXIDE	RE-.56006-GP	RMF 2W 5.6 OHM 5%
4719-821J-1-X	RMF 2W 820R 5% AL METALO	RE-082009-GP	820 OHM,5 PCNT,2W,RMF AL METALO,,
471A-022J-5-N	RMF 3W 0.22R 5% RL RGC3	RE-.02202-GP	0.22 5% 3W THICK FILM
471A-022K-5-N	RMF 3W 0.22R 10% RL RGC3	RE-.02201-GP	0.22 OHM 5% 3W THK FLM
471B-102J-1-X	RMF 5W 1K 5% AL METAL OXIDE	RE-110011-GP	RMF 5W 1K 5%
471B-120J-1-X	RMF 5W 12R 5% AL METAL OXIDE	RE-001201-GP	12 5% 5W METAL OXIDE FILM
471B-121J-1-X	RMF 5W 120R 5% AL METAL	RE-012006-GP	120 5% 5W METAL FILM
471B-202J-1-X	RMF 5W 2K 5% AL METAL OXIDE	RE-120007-GP	RMF 5W 2K 5% AL METAL
471B-222J-1-X	RMF 5W 2.2K 5% AL METAL OXIDE	RE-122008-GP	RMF 5W 2.2K 5% METAL
471B-302J-1-X	RMF 5W 3K 5% AL METAL OXIDE	RE-130003-GP	RMF 5W 3K 5% METAL
471B-392J-1-X	RMF 5W 3.9K 5% AL METAL	RE-139004-GP	RMF 3.9K 5% 5W AL METAL
471B-512J-1-X	RMF 5, 1K 5% AL METAL OXIDE	RE-151003-GP	RMF 5W 5.1K 5% AL METAL
471B-821J-1-X	RMF 5W 820R 5% AL METAL OXIDE	RE-082005-GP	RMF 5W 820 OHM 5% AL METAL
471B-822J-1-X	RMF 5W 8, 2K 5% AL METAL OXIDE	RE-182002-GP	RMF 5W 8.2K 5% AL METAL
4720-100A-J	RMG 1/10W 10R 1% 0805	RE-001006-GP	10,1 PCNT,1/10W,THICK FILM,0805,100V
4720-101A-J	RMG 1/10W 100R 1% 0805	RE-010011-GP	100 1% 1/10W THK FLM 0805 100V
4720-101J-J	RMG 1/10W 100R 5% 0805	RE-010006-GP	RMG 1/10W 100 5%
4720-102A-J	RMG 1/10W 1K 1% 0805	RE-110013-GP	RMG 1/10W 1K 1% 0805
4720-102J-J	RMG 1/10W 1K 5% 0805	RE-110012-GP	RMG 1/10W 1K 5% 0805
4720-103A-J	RMG 1/10W 10K 1% 0805	RE-210007-GP	10K 1% 1/10W THK FLM 0805
4720-103J-J	RMG 1/10W 10K 5% 0805	RE-210006-GP	RMG 1/10W 10K 5% 0805
4720-104A-J	RMG 1/10W 100K 1% 0805	RE-310007-GP	100K 1% 1/10W THK FLM 0805
4720-113A-J	RMG 1/10W 11K 1% 0805	RE-211001-GP	RMG 1/10W 11K 1% 0805
4720-1181-J	RMG 1/10W 1.18K 1% 0805	RE-111801-GP	1.18K,1 PCNT,1/10W,RMG,0805,
4720-1212-J	RMG 1/10W 12.1K 1% 0805	RE-212105-GP	12.1K,1 PCNT,1/10W,RMG,0805,
4720-122A-J	RMG 1/10W 1.2K 1% 0805	RE-112001-GP	RMG 1/10W 1.2K 1% 0805
4720-123A-J	RMG 1/10W 12K 1% 0805	RE-212003-GP	12K 1% 1/10W THK FLM 0805 100V
4720-152A-J	RMG 1/10W 1.5K 1% 0805	RE-115008-GP	1.5K,1 PCNT,1/10W,THK FLM,0805,100V
4720-152J-J	RMG 1/10W 1.5K 5% 0805	RE-115004-GP	RMG 1/10W 1.5K 5% 0805
4720-1542-J	RMG 1/10W 15.4K 1% 0805	RE-215402-GP	15.4K,1 PCNT,1/10W,RMG,0805,
4720-182A-J	RMG 1/10W 1.8K 1% 0805	RE-118001-GP	1.8K,1 PCNT,1/10W,THK FILM,0805,

Continued on next page ➜

Table 1, continued. RMX and ISA part updates

Original Part #	Description	New Part #	Description
4720-201A-J	RMG 1/10W 200R 1% 0805	RE-020003-GP	200 1% 1/10W THK FLM 0805 100V
4720-202A-J	RMG 1/10W 2K 1% 0805	RE-120004-GP	RMG 1/10W 2K 1% 0805
4720-202J-J	RMG 1/10W 2K 5% 0805	RE-120004-GP	RMG 1/10W 2K 1% 0805
4720-203A-J	RMG 1/10W 20K 1% 0805	RE-220005-GP	RMG 1/10W 20K 1% 0805
4720-203J-J	RMG 1/10W 20K 5% 0805	RE-220005-GP	RMG 1/10W 20K 1% 0805
4720-222A-J	RMG 1/10W 2.2K 1% 0805	RE-122010-GP	2.2K 1% 1/10W THK FM 0805 100V
4720-223A-J	RMG 1/10W 22K 1% 0805	RE-222001-GP	22K 1% 1/10W 0805
4720-224J-J	RMG 1/10W 220K 5% 0805	RE-322002-GP	RMG 1/10W 220K 5% 0805
4720-243A-J	RMG 1/10W 24K 1% 0805	RE-224001-GP	24.0K 1% 1/10W THK FLM 0805
4720-243J-J	RMG 1/10W 24K 5% 0805	RE-224001-GP	24.0K 1% 1/10W THK FLM 0805
4720-271A-J	RMG 1/10W 270R 1% 0805	RE-027004-GP	RMG 1/10W 270 OHM 1% 0805
4720-271J-J	RMG 1/10W 270R 5% 0805	RE-027003-GP	RMG 1/10W 270 OHM 5%
4720-273A-J	RMG 1/10W 27K 1% 0805	RE-227001-GP	27K 1% 1/10W 0805
4720-2740-J	RMG 1/10W 274R 1% 0805	RE-027403-GP	274 1% 1/10W THICK FILM 0805
4720-3011-J	RMG 1/10W 3.01K 1% 0805	RE-130103-GP	RMG 1/10W 3.01K 1% 0805
4720-301A-J	RMG 1/10W 300R 1% 0805	RE-030006-GP	300 OHM,1 PCNT,1/10W,THICK FILM,0805,
4720-332J-J	RMG 1/10W 3.3K 5% 0805	RE-133007-GP	RMG 1/10W 3.3K 5% 0805
4720-390A-J	RMG 1/10W 39R 1% 0805	RE-003901-GP	RMG 1/10W 39 OHM 1% 0805
4720-391A-J	RMG 1/10W 390R 1% 0805	RE-039002-GP	390 1% 1/10W THK FLM 0805 100V
4720-393A-J	RMG 1/10W 39K 1% 0805	RE-239003-GP	39K,1 PCNT,1/10W,MET FLM,0805,100V
4720-393J-J	RMG 1/10W 39K 5% 0805	RE-239001-GP	RMG 1/10W 39K 5% 0805
4720-4643-J	RMG 1/10W 464K 1% 0805	RE-346402-GP	464K 1% 1/10W THK FLM 0805 50V
4720-470A-J	RMG 1/10W 47R 1% 0805	RE-004704-GP	47 1% 1/10W THK FLM 0805
4720-470J-J	RMG 1/10W 47R 5% 0805	RE-004702-GP	RMG 1/10W 47 OHM 5% 0805
4720-472A-J	RMG 1/10W 4.7K 1% 0805	RE-147002-GP	4.7K 1% 1/10W THK FLM 0805
4720-472J-J	RMG 1/10W 4.7K 5% 0805	RE-147001-GP	RMG 1/10W 4.7K 5% 0805
4720-473A-J	RMG 1/10W 47K 1% 0805	RE-247006-GP	47K 1% 1/10W THK FLM 0805 100V
4720-474J-J	RMG 1/10W 470K 5% 0805	RE-347003-GP	RMG 1/10W 470K 5% 0805
4720-47R5-J	RMG 1/10W 47.5R 1% 0805	RE-247504-GP	47.5R,1 PCNT,1/10W,RMG,0805,
4720-592A-J	RMG 1/10W 5.9K 1% 0805	RE-159003-GP	5.9K 1% 1/10W THK FLM 0805
4720-6040-J	RMG 1/10W 604R 1% 0805	RE-060402-GP	RMG 1/10W 604OHM 1% 0805
4720-621A-J	RMG 1/10W 620R 1% 0805	RE-062001-GP	620 1% 1/10W THK FLM 0805
4720-6491-J	RMG 1/10W 6.49K 1% 0805	RE-164901-GP	6.49K,1 PCNT,1/10W,RMG,0805,
4720-6981-J	RMG 1/10W 6.98K 1% 0805	RE-169802-GP	6.98K,1 PCNT,1/10W,THK FLM,0805,100V
4720-750J-J	RMG 1/10W 75R 5% 0805	RE-007506-GP	RMG 1/10W 75 OHM 5% 0805
4720-752A-J	RMG 1/10W 7.5K 1% 0805	RE-175004-GP	7.5K 1% 1/10W THK FM 0805 100V
4720-752J-J	RMG 1/10W 7.5K 5% 0805	RE-175003-GP	RMG 1/10W 7.5K 5% 0805
4720-7870-J	RMG 1/10W 787R 1% 0805	RE-078702-GP	787 1% 1/10W THICK FILM 0805
4720-821A-J	RMG 1/10W 820R 1% 0805	RE-082007-GP	820 1% 1/10W THK FLM 0805
4721-100J-6	RMG 1/8W 10R 5% 1206	RE-001009-GP	10 1% 1/8W THK FLM 1206
4721-101A-6	RMG 1/8W 100R 1% 1206	RE-010012-GP	100 1% 1/8W THK FLM 1206
4721-102A-6	RMG 1/8W 1K 1% 1206	RE-110015-GP	1K,1 PCNT,1/8W,THK FLM,1206,200V
4721-104A-6	RMG 1/8W 100K 1% 1206	RE-310008-GP	100K 1% 1/8W THK FLM 1206
4721-105J-6	RMG 1/8W 1M 5% 1206	RE-410002-GP	RMG 1/8W 1M 5% 1206
4721-152A-6	RMG 1/8W 1.5K 1% 1206	RE-115006-GP	1.5K 1% 1/8W THK FLM 1206
4721-154A-6	RMG 1/8W 150K 1% 1206	RE-315004-GP	RMG 1/8W 150K 1% 1206
4721-154J-6	RMG 1/8W 150K 5% 1206	RE-315003-GP	RMG 1/8W 150K 5% 1206
4721-184A-6	RMG 1/8W 180K 1% 1206	RE-318002-GP	180K 1% 1/8W THK FLM 1206
4721-224J-6	RMG 1/8W 220K 5% 1206	RE-322001-GP	RMG 1/8W 220K 5% 1206
4721-302A-6	RMG 1/8W 3K 1% 1206	RE-130004-GP	RMG 1/8W 3K 1% 1206
4721-333J-6	RMG 1/8W 33K 5% 1206	RE-233001-GP	RMG 1/8W 33K 1% 1206
4721-334J-6	RMG 1/8W 330K 5% 1206	RE-330001-GP	RMG 1/8W 330K 5% 1206
4721-390A-6	RMG 1/8W 39R 1% 1206	RE-003902-GP	39 1 PCNT 1/8W THK FLM 1206
4721-394J-6	RMG 1/8W 390K 5% 1206	RE-339001-GP	RMG 1/8W 390K 5% 1206
4721-4643-6	RMG 1/8W 464K 1% 1206	RE-346401-GP	464K 1% 1/8W THK FLM 1206
4721-473J-6	RMG 1/8W 47K 5% 1206	RE-247004-GP	RMG 1/8W 47K 5% 1206
4721-474J-6	RMG 1/8W 470K 5% 1206	RE-347002-GP	RMF 1/8W 470K 5% ATS
4721-4993-6	RMG 1/8W 499K 1% 1206	RE-349901-GP	499K 1% 1/8W THICK FILM 1206

Continued on next page ➜

Table 1, continued. RMX and ISA part updates

Original Part #	Description	New Part #	Description
4721-4R7A-6	RMG 1/8W 4.7R 1% 1206	RE-.47002-GP	4.7 1% 1/8W METAL FILM 1206
4721-6340-6	RMG 1/8W 634R 1% 1206	RE-063404-GP	634 OHMS 1% 1/8W 1206
4721-682J-6	RMG 1/8W 6.8K 5% 1206	RE-168002-GP	RCF 1/8W 6.8K 5% ATS
4721-683A-6	RMG 1/8W 68K 1% 1206	RE-268003-GP	RMG 1/8W 68K 1% 1206
4721-821A-6	RMG 1/8W 820R 1% 1206	RE-082008-GP	820 1% 1/8W THK FLM 1206 200V
4721-821J-6	RMG 1/8W 820R 5% 1206	RE-082003-GP	RMG 1/8W 820 OHM 5% 1206
4750-5540-0	VR VOL.2.5K 11 DETENTS	PT-225002-GP	VR VOL. 2.5K,11 DETENTS, D-SHAFT,,,,
4750-6200-0	VR V012CPH, D-SHAFT 10K LINEAR B	PT-310006-GP	VR V012CPH, D-SHAFT 10K
4751-0110-0	VR, 2.5K, D-SHAFT	PT-225000-GP	RES VAR 2.5K RT ANGLE PCB
4751-0420-0	VR RV06002-23E3-20FW-	PT-225001-GP	GAIN 2.5K 20% .1W RT ANG SHAFT
4756-1016-3-06	SVR H6 100R RH0615C	PT-110002-GP	TRIM POT,100 OHM,20 PCNT,0.15W,,
4756-2226-3-06	SVR 2.2K H3 7X7.6 R0615C	RE-122006-GP	SVR 2.2K H3 7X7
4804-0010-2	DIODE 1N4001 AT	QD-000280-GP	DIODE 1N4001 ELE-DO002
4804-0020-5	DIODE UF4002 RL D0-41	QD-000273-GP	DIODE RECTIFIER,100V,1A,,MUR110,DO-41,
4804-0040-1	DIODE IN4004 AL	QD-000202-GP	DIODE 1N4004 AL
4804-0040-2	IN 4004 AL	QD-000202-GP	DIODE 1N4004 AL
4804-1480-2	DIODE 1N4148 AT	QD-000262-GP	DIODE 75V 1N4148 DO-35 4NS
4804-1480-3	DIODE LL4148 SM	QD-000201-GP	DIODE LL4148 SM
4804-9340-2	DIODE IN4934 AT	QD-000206-GP	DIOD RECT FAST, IN4934 AT
4805-4040-1	DIODE 1N5404 3A 400V	QD-000217-GP	DIODE,400V,3A,IN5404,DO-201AD
4837-3B20-2	DZ 1/2W 3.8-4.0V AT	QD-000218-GP	DIOD ZNR 3.8-4.0V 1/2 HZ SER
4837-5B10-2	DZ 1/2W 5.5-5.8V AT	QD-000212-GP	DIODE ZENER 1/2W 5.5-5.8V
4837-7C51-2	DZ 1/2W 7.29~7.67V ROHM	QD-000256-GP	DIOD ZNR 7.29-7.67V,1/2W HZ
4838-10V6-2	DZ 1,3W 10V AT TEMIC	QD-000219-GP	DIODE ZENER 1.3W 10V TEMIC
4838-12V6-2	DZ 1W 12V AT TEMIC	QD-000220-GP	DIODE ZENER 1W 12V AT TEMIC
4838-15V6-2	DZ 1W 15V AT TEMIC	QD-000203-GP	DIOD ZNR 15V 1W SILICON EPIT
4840-1760-0	DIODE RECT 1A 200V DB103 RECTRON	QD-000200-GP	DIODE RECT 1A 200V DB103
4840-2150-0	BRIDGE RECTIFIER 400V 25A	QD-000227-GP	BRIDGE RECT 400V 25A
4840-2190-0	DIOD 200V 15A 35NS MUR1520	QD-000215-GP	DIODE MUR1520 15A 200V
4840-8630-0	DIODE BRIDGE RECTIFIER	QD-000257-GP	BRDG RECT 400V 35A IN-LINE
4851-987R-5	TR 2SA1987 TO-3P PNP	QD-000278-GP	TRANSISTOR PNP,260V,15A,180W,2SA1987(QSCA),TO-264,
4853-9060-3	OBS-TR 3906 PNP SM	QD-000205-GP	XISTOR PNP 40V 0.2A TR3906 SOT-23
4855-359R-5	TR 2SC5359 TO-3P NPN	QD-000277-GP	TRANSISTOR NPN,260V,15A,180W,2SC5359 (QSCA),TO-264,
4856-02AR-3	TR 2SD602AR NPN SMD	QD-000274-GP	SRV-TRANSISTOR NPN,40V,0.5A,0.2W,2SD0602A,SOT-23,
4857-10AR-3	TR 2SB710AR PNP SMD	QD-000275-GP	SRV-TRANSISTOR PNP,40V,0.5A,0.2W,2SB0710A,SOT-23,
485T-A420-3	TR MMBTA42 NPN SMD,,,,,SOT-23,	QD-000308-GP	TR MMBTA42 NPN SMD,,,,,SOT-23,
4860-0640-3	TR 3904 HFE 100-300SM	QD-000204-GP	XISTOR NPN 60V 200MA 3904 SOT-23
4860-2620-5	TR TIP31C SAMSUNG	QD-000214-GP	TR TIP31C SAMSUNG
4860-3250-5	FET TR RFP50N06	QD-000222-GP	SRV-TR RFP50N06 N-CH PWR
4860-5020-5	OBS-TR MJE15032	QD-000207-GP	XISTOR NPN 250V 0.5A MJE15032
4860-5030-5	OBS-TR MJE15033	QD-000210-GP	XISTOR PNP 250V MJE15033
4860-5110-3	TR KST42	QD-000213-GP	TR KST42
4860-5360-3	TR MMBTA92 SOT 23 KEC,,,,,,	QD-000311-GP	TR MMBTA92 SOT 23 KEC,,,,,,
4860-8890-0	TR MPS A06 VCE 80V NS	QD-000211-GP	TR MPS A06VCE 80V NS
4901-4070-5	MOSFET IRF1407 75V 130A	QD-000276-GP	MOSFET N CHANNEL,75V,75A,300W,IRF1407,TO-220,
4902-N06X-5	FET MTP52N06V N-CH PWR	QD-000260-GP	MOSFET,N-CH,60V,52A,52N06V
490F-Z440-5	FETN 60V 50A 150W	QD-000347-GP	FETN,60V,50A,150W,,,
5100-1030-3A	FUSE T10A 125V/250V (UL/CSA)	MS-000129-GP	FUSE T10A/125V/250V
5120-0018-0	FU T1A 250V SEMKO/UDE,5X20MM	MS-000220-GP	FUSE T1A 250V SEM/UDE 5X20MM
5120-0061-0	FUSE T12A/250V 6.3X32MMU	MS-000124-GP	FUSE 12A 250V 6.3 X 32MM
5120-0096-0	FUSE T30A 250V 6.4VX32MM	MS-000189-GP	30A 250V 6.4MM X 32MM FAST
5200-3531-0	CIRCUIT BREAKER 15A	SW-000091-GP	CIRCUIT BREAKER 15A
5200-4713-0	10 POLE DIP SWITCH (TALL)	SW-000089-GP	10 POLE DIP SWITCH
5200-4717-0	ROCKER POWER SWITCH 125V/20A & 250V/15A	SW-000088-GP	ROCKER POWER SWITCH
5200-4730-0	CIRCUIT BREAKER 5A	SW-000093-GP	CIRCUIT BREAKER,5 AMP,,
5200-4731-0	CIRCUIT BREAKER 8A	SW-000094-GP	CIRCUIT BREAKER 8A
5200-4822-0	SWITCH ROCKER POWER DPST	SW-000097-GP	DPST,20A,125VAC
5200-4826-0	ROCKER POWER SWITCH SPST,125V/20A,250V16A	SW-000088-GP	ROCKER POWER SWITCH

Continued on next page ➜

Table 1, continued. RMX and ISA part updates

Original Part #	Description	New Part #	Description
5200-4858-0	CIRCUIT BREAKER 20A	SW-000102-GP	CIRCUIT BREAKER 20A
5200-4926-0	ROCKER POWER SWITCH SPST	SW-000165-GP	SWITCH,ROCKER POWER SPST,,
5202-0003-1	THERMAL MTC 10K RED WIRE	WC-000368-GP	WIRE,THERMAL NTC 10K RED,,,,,
5400-0831-0	HEATSINK (214) 20MM-HIGH HOLE	MS-000126-GP	HEATSINK, BRIDGE RECTIFIER
5400-1831-0	HEATSINK FOR RECTIFIER	MS-000125-GP	HEATSINK FOR RECTIFIER
5400-1831-1	HEATSINK FOR RECTIFIER	MS-000125-GP	HEATSINK FOR RECTIFIER
5400-3332-1	HEAT SINK 280 VARY HOLES	CH-000164-GP	HEATSINK ISA280/450
5400-3342-1	HEATSINK 750 VARY HOLES	CH-000163-GP	HEATSINK ISA 750 3 SP
5400-3591-0	HEAT SINK 3550	CH-000232-GP	HEATSINK RMX 4050HD
5400-3731-0	HEATSINK H40 20MM HIGH	MS-000193-GP	HEATSINK,BRIDGE RECTIFIER,40MM,,
5400-4122-0	HEAT SINK QZ020C	CH-000818-GP	HEATSINK,LEFT,,RMX1450,
6360-0012-0	PLASTIC CABLE TIE (BLK)	PL-000152-GP	CABLE TIE, ISA
7009-8620-0	AC POWER CORD RMX (EXPORT)	WC-000213-GP	AC CORD,HPR153F,230V
7010-2226-0	UL1015 #14 2P GREEN	WC-000177-GP	UL1015 #14 2P GRN L=100
7010-2234-1	GRND WIRE UL1015 #14	WC-000198-GP	GROUND WIRE
7010-2254-1	CONN.ASSY AW14 L=340mm	WC-000167-GP	CONN AWG14 L-440 BRN W/1TRND
7010-2289-0	CONN.ASSY 3PIN	WC-000170-GP	OBS-CONN ASSY 3-PIN (SHIELDED)
7010-2316-0	UL1015 #14 3P BROWN	WC-000378-GP	WIRE,UL1015 #14 3P BROWN,,,,,
7010-2317-0	UL1015 #14 2P OFFWHITE	WC-000384-GP	UL1015,OFFWHITE,#14,2P,,L=300,
7010-2318-0	UL1015 #14 3P BROWN	WC-000378-GP	WIRE,UL1015 #14 3P BROWN,,,,,
7010-2319-0	UL1015 #14 2P OFF WHITE	WC-000385-GP	UL1015,OFFWHITE,#14,2P,,L=360,
7010-2328-0	GRND WIRE UL1015 #14 L=	WC-000381-GP	GRND WIRE UL 1015 #14L,,,,,,
7010-9630-0	CONN . WIRE 13P P2.0 L=240	WC-000182-GP	CONN ASSY 13P P2.0 L=240
7010-9640-0	AC POWER CABLE 15A, 14 AWG, (ISA)	WC-000181-GP	AC CORD 15A, 14 AWG, ISA/RMX
7010-9651-0	CONN.WIRE (RED) #14 W/SPADE TERMINAL L=150	WC-000451-GP	CONN. WIRE,RED,#14,W/SPADE TERMINAL,,L=150,
7010-9652-0	CONN. WIRE (WHITE) #14 W/SPADE TERMINAL L=150	WC-000225-GP	CONN WIRE #14 WHT
7010-9653-0	CONN WIRE (GREY) #14 W/SPADE TERMINAL L=250	WC-000226-GP	CONN WIRE #14 GRY
7010-9660-0	CONN. WIRE #14 W/SPADE TERMINAL (BLACK) L=430mm	WC-000234-GP	CONN WIRE #14 W/SPADE BLK
7010-9661-0	CONN. WIRE #14 W/SPADE TERMINAL (RED) L=430mm	WC-000231-GP	CONN WIRE #14 W/SPADE RED
7010-9662-0	CONN WIRE #14 W/SPADE TERMINAL (WHITE) L=380mm	WC-000227-GP	CONN WIRE #14 W/SPADE
7010-9663-0	CONN. WIRE (GREY) # 14 W/SPADE TERMINAL L=450	WC-000228-GP	CONN WIRE #14 GRY
7010-9664-0	CONN. WIRE (BROWN) # 14W/SPADE TERMINAL L=450	WC-000186-GP	WIRE 1015 BROWN #14
7010-9670-0	UL 1015 # 14 W/RING TERMINAL (GREEN)	WC-000218-GP	CONN,WIRE,#14,GREEN,RMX,UL 1015,
7010-9820-0	CONN. WIRE (BLACK) # 16W/S	WC-000386-GP	CONN. WIRE,BLACK,#16 W/S,,,,
7010-9821-0	CONN. WIRE (RED)#16W/SPA	WC-000387-GP	CONN. WIRE,RED,#16 W/SPA,,,,
7010-9822-0	CONN. WIRE (WHITE)#16 W/S	WC-000388-GP	CONN. WIRE,WHITE,#16 W/S,,,,
7010-9823-0	CONN. WIRE (GREY)#16 W/SP	WC-000443-GP	OBS-CONN. WIRE,GRAY,#16 W/SP,,,,
7010-9830-0	CONN. WIRE (BLACK)#16W/S	WC-000444-GP	CONN. WIRE,BLACK,#16 W/S,,,,
7010-9831-0	CONN. WIRE(RED)# 16W/SPA	WC-000445-GP	CONN. WIRE,RED,#16 W/SPA,,,,
7010-9832-0	CONN. WIRE (WHITE) # 16 W/S	WC-000446-GP	CONN. WIRE,WHITE,#16 W/S,,,,
7010-9833-0	CONN. WIRE (GREY)#16 W/SP	WC-000447-GP	OBS-CONN. WIRE,GRAY,#16 W/SP,,,,
7010-9834-0	CONN. WIRE (BROWN)#16W/S	WC-000448-GP	CONN. WIRE,BROWN,#16 W/S,,,,
7010-9860-0	26 PIN IEC RIBBON CABLE L=320MM	WC-000194-GP	RIBBON CABLE 26 PIN IEC
7010-9870-0	CONN. WIRE #14 W/SPADE TERMINAL L=250MM	WC-000235-GP	CONN,WIRE,#14 W/SPADE,GREEN,,,
7010-9960-0	CONN. WIRE UL1015#16L=60	WC-000449-GP	CONN. WIRE,UL 1015,#16,,,L=60,
7012-5420-0	CONN. ASSY 13 PINS 2.5PL=	WC-000191-GP	CONN ASSY,13 PINS,2.5P,,,,
7012-5440-0	CONN ASSY GND WIRE	WC-000223-GP	CONN ASSY GROUND WIRE
7012-6325-0	WIRE ASSY W/2T L=100MM	WC-000282-GP	WIRE ASSY,14AWG,100MM,L BRN
7012-6327-0	WIRE ASSY W/1T L=460MM	WC-000283-GP	WIRE ASSY W/1T L=460MM
7012-6328-0	WIRE ASSY W/2T L=600MM	WC-000284-GP	WIRE ASSY W/2T L=600MM
7012-6329-1	WIRE CON ASSY W/6 SINGLE	WC-000285-GP	WIRE CONN ASSY W/6 SINGLE
7012-6332-0	CONN.ASSY 6 PIN SHIELD	WC-000286-GP	WIRE ASSY,28AWG,6COND,140MM L.
7012-6344-1	GRND WIRE UL1015 #14	WC-000287-GP	GND WIRE UL 1015 #14
7012-6344-1	GRND WIRE UL1015 #14	WC-000412-GP	OBS-GRND WIRE,UL1015 #14,,,,,
7012-6345-0	UL1015 #14 3P BROWN	WC-000288-GP	WIRE ASSY,14AWG,210MM,L,BRN
7012-6346-0	UL1015 #14 W/1 TERMINAL	WC-000289-GP	WIRE ASSY,14AWG,600MM L,BLU
7012-6396-0	CONN ASSY 7PIN SHIELD	WC-000290-GP	WIRE ASSY,28AWG,7COND,140MM L.
7012-6397-0	WIRE ASSY W/2T L=170MM	WC-000291-GP	WIRE ASSY,14AWG,170MM,L BRN

Continued on next page ➜

Table 1, continued. RMX and ISA part updates

Original Part #	Description	New Part #	Description
7012-6401-0	CABLE ASSY RIBBON 28PIN	WC-000292-GP	CABLE ASSY RIBBON 28PIN
7012-6409-0	WIRE W/2T 1ANGLE TER L=5	WC-000293-GP	WIRE ASSY,14AWG,1COND,500MM WT
7012-6410-0	WIRE W/2T 1ANGLE TER L=4	WC-000294-GP	WIRE ASSY,14AWG,1COND,430MM WT
7012-6433-0	WIRE CON ASSY W/1RING	WC-000295-GP	WIRE ASSY,GRAY 60MM
7012-6434-0	WIRE CON ASSY W/3TER #14	WC-000300-GP	WIRE ASSY,14AWG,320MM,L,BRN
7012-6435-0	WIRE CON ASSY W/2TER #14	WC-000299-GP	WIRE ASSY,14AWG,1COND,460MM BL
7012-6436-0	WIRE CON ASSY W/1TER #14	WC-000302-GP	WIRE ASSY,14AWG,150MM L,BLU
7012-6437-0	WIRE CON ASSY W/1TER #14	WC-000303-GP	WIRE ASSY,14AWG,150MM L,BRN
7012-6482-0	WIRE ASSY W/2T L=600MM	WC-000330-GP	WIRE ASSY W/2T L-600MM #14 BRN
7012-6519-0	AC POWER CORD, 120V, RMX5050	WC-000323-GP	AC CORD 20A, RMX 5050 (120v)
7012-6520-0	AC POWER CORD, 230V, RMX5050	WC-000324-GP	AC CORD RMX5050 CE
7012-6696-0	WIRE ASSY #14 OFF WHITE,W/3T L=	WC-000331-GP	WIRE ASSY W/3T L=490/100 #14
7012-6697-0	WIRE ASSY #14 OFF WHITE,W/3T L=	WC-000332-GP	WIRE ASSY W/3T L-560/100 #14
7012-6698-0	WIRE ASSY #14 BROWN,W/2T =260	WC-000333-GP	WIRE ASSY W/2T L=260 #14 BRN
7012-6699-0	WIRE ASSY #14 DROWN,W/2T L=220	WC-000334-GP	WIRE ASSY W/2T L-220 #14 BRN
7012-6700-0	WIRE ASSY #14 GREY,W/2T L=520	WC-000335-GP	WIRE ASSY W/2T L-520 #14 GRY
7012-6764-0	CONN ASSY #26 WITH SHRINKAGE	WC-000450-GP	CONN ASSY,,#26,,,,
7602-1120-2004	CONN ASSY 2P P=2.5 L=120	WC-000296-GP	WIRE ASSY,26AWG,2COND,120MM L.
7602-1580-2004	CONN.WIRE ASSY 2PIN	WC-000169-GP	CONN ASSY 2PIN ISA
7603-1160-2004	CON ASSY #26,3P P2.5, L=160MM	WC-000337-GP	CONN ASSY 3P P2.5 L-160 26AWG
7603-1360-2004	AWG#26 CONN.ASSY 3P	WC-000171-GP	CONN ASSY 3-PIN
7604-1100-2004	CONN.ASSY 4P P=2.5 L=100	WC-000172-GP	OBS-CONN ASSY 4-PIN
7604-1200-2004	CONN.ASSY 4P P2.5 L=200	WC-000173-GP	CONN ASSY 4P P2.5 L=200 AWG26
7606-1100-2004	CONN ASSY 6P P2.5 L=100	WC-000174-GP	CONN ASSY 6-PIN ISA 280
7608-1460-2004	CONN.ASSY 8P P2.5 L=460	WC-000175-GP	CONN ASSY 8P P2.5 L=460 AWG26
7703-1220-2004	CONN. ASSY 3P P2.5 L=220	WC-000242-GP	CONN ASSY 3P W/OPEN END
8900-2165-1	DC FAN 24V 119x119x38mm	MS-000122-GP	DC FAN, 24V 119X119X38MM
8900-2179-0	X'FER MOUNTING ASSY	WP-000068-00	SRV - XFMR MNTG ASSY ISA SERIES
8900-2180-0	X'FER MOUNTING ASSY	WP-000069-00	SRV - XFMR MNTG ASSY ISA300/500/800T
8900-2195-0	SCREW 4x10mm	SC-040002-GP	OBS-SCREW,M4X10(H) BLK,ZN,SERRATED
8900-2195-0	SCREW 4x10mm	SC-040008-GP	P/P,M4,10MM,BLK,TRIANGULAR TIP
8900-2195-1	SELF SCREW 4X10 WITH	SC-040002-GP	OBS-SCREW,M4X10(H) BLK,ZN,SERRATED
8900-2198-0	MACHINE SCREW M4X20 WITH	SC-040007-GP	PHILLIPS,SERRATED M4X20L BLK
8901-2930-0	X'FER MOUNTING ASSY	WP-000076-00	SRV - XFMR MOUNTING HARDWARE (NUT,BOLT,WASHER)
8901-4670-1	X'FER MOUNTING ASSY	NW-080003-GP	NUT M8X13MM 6.5MM THK STL WHT
8910-0062-0	CE 80V 4700U 20 % RL 25X5	CA-847001-GP	CE 80V 4700UF 20% RL 25X
8910-0272-0	CE 100V 3300U 20% 25X50	CA-833002-GP	3300UF 20% 100V ELECT RAD
8910-0273-0	POLYSWITCH 0.15 ohm 1.1A 1.5W	RE-000005-GP	POLYSWITCH 1.1A 0.15 OHM 1.5W
8910-0274-0	THERMAL PTC 60C 100 OHM	RE-000260-GP	THERMAL PTC 60C 100 OHM
8910-0275-0	THERMAL NTC 30A 1 ohm	RE-000270-GP	NTC 30A 1 OHM
8910-0482-0	TRIAC 600V 40A MAC224A8	QD-000221-GP	SRV-TRIAC 600V 40A MAC224 A8
8910-0488-0	ROD THERMISTOR NTC 50ohm	RE-000250-GP	NTC RES 50 OHM
8910-0494-0	CE 63V 12000UF 20% RL	CA-912001-GP	12000UF,20 PCNT,63V,CE,RL,,
8910-0578-0	THERMAL NTC 15A 4 OHM	RE-000290-GP	NTC, 4.0 OHM, 14A, 20%
8910-0579-0	CE 63V 12000uF 20% RL	CA-912002-GP	12000UF,20 PCNT,63V,RL30X50,LS NOVER HI-RIPPLE,
8910-0599-0	TRIAC BTA41-600B	QD-000261-GP	TRIAC 600V 40A BTA41-600B,TOP3
8910-0600-0	CC 280V 0.47UF 10% RL	CA-447010-GP	.47UF,10 PCNT,280V,CC,RL 32X11X20MM,
8913-4000-0	OBS-DC FAN 24V 119X119X38MM	MS-000191-GP	FAN,24VDC, 119 X 119 X 38MM
PCB-I45011+PWR2	PCB ASSY,MAIN,BOTTOM,ISA450,NON T VERSION	WP-004505-00	PCB ASSY,MAIN,BOTTOM,ISA450,NON T VERSION
PCB-QZ010C-INP	SRV - PCB ASSY INPUT QZ010C	WP-008509-00	PCB ASSY,INPUT,RMX850,,
PCB-QZ010C-PSU	SRV - PCB ASSY POWER UNITQZ010C	WP-008502-00	PCB ASSY,AC PCB,RMX850/1450
PCB-QZ010C-PWR1	SRV - PCB ASSY POWER (L), RMX850	WP-008503-00	PCB ASSY,PWR MOD, LT,RMX850,,
PCB-QZ010C-PWR2	SRV - PCB ASSY POWER (R), RMX850	WP-008504-00	PCB ASSY,PWR MOD,RT,RMX850,,W/GAIN POTS
PCB-QZ020C-PWR1	SRV - PCB ASSY POWER (L), RMX1450	WP-014502-00	PCB ASSY,PWR MOD,LT,RMX1450,,
PCB-QZ020C-PWR2	SRV - PCB ASSY POWER (R), RMX1450	WP-014503-00	PCB ASSY,PWR MOD,RT,RMX1450,,W/GAIN POTS
PCB-QZ030C-INP	SRV - PCB ASSY INPUT BOARD QZPO30C	WP-002455-00	PCB ASSY,INPUT,RMX2450,,
PCB-QZ030C-OUT	SRV - PCB ASSY OUTPUT BOARD QZ030C	WP-002452-00	PCB ASSY,BINDING POST/SPEAKON OUTPUT,RMX2450,,
PCB-QZ030C-PWR1	SRV - PCB ASSY POWER (RIGHT, W/GAIN POTS), RMX2450	WP-002453-00	PCB ASSY,PWR MOD,RT,RMX2450,,W/GAIN POTS

Continued on next page ➜

Table 1, continued. RMX and ISA part updates

Original Part #	Description	New Part #	Description
PCB-QZ030C-PWR2	SRV - PCB ASSY POWER (LEFT, WITHOUT GAIN POTS), RMX2450	WP-002454-00	PCB ASSY,PWR MOD,LT,RMX2450,,
PCB-QZ040C-INP	SRV - PCB ASSY INPUT QZ040C	WP-004502-00	PCB ASSY,INPUT,ISA280/450,,
PCB-QZ040C-INP1	SRV - PCB ASSY INPUT HD-15	WP-002805-00	PCB ASSY,DATAPORT,ISA280,,
PCB-QZ040C-PSU	SRV - PCB ASSY POWER UNIT	WP-002807-00	PCB ASSY,AC,ISA280/300TI,120V,
PCB-QZ040C-PWR1	SRV - PCB ASSY POWER (L)	WP-002802-00	PCB ASSY,MAIN,TOP,ISA280/300TI,
PCB-QZ040C-PWR2	SRV - PCB ASSY POWER (R)	WP-002801-00	PCB ASSY,MAIN,BOTTOM,ISA280,
PCB-QZ050C-PSU	SRV - PCB ASSY POWER UNIT	WP-004504-00	PCB ASSY,AC,ISA450/500TI,120V,
PCB-QZ050C-PWR1	SRV - PCB ASSY POWER (L), ISA450 / ISA500T	WP-004501-00	PCB ASSY,MAIN,TOP,ISA450/500TI,,
PCB-QZ050C-PWR2	SRV - PCB ASSY , ISA450 (R)	WP-004505-00	PCB ASSY,MAIN,BOTTOM,ISA450,NON T VERSION
PCB-QZ060C-INP	SRV - PCB ASSY INPUT QZ060C	WP-007502-00	PCB ASSY,INPUT,ISA750/800TI,,
PCB-QZ060C-PSU	SRV - PCB ASSY POWER UNIT	WP-007506-00	PCB ASSY,AC,ISA750/800TI,120V,
PCB-QZ060C-PWR1	SRV - PCB ASSY POWER (L)	WP-007501-00	PCB ASSY,MAIN,ISA750,,BOTTOM
PCB-QZ060C-PWR2	SRV - PCB ASSY POWER (R)	WP-000826-00	PCB ASSY,MAIN,TOP,ISA750/800TI,CHANNEL 2
PCB-QZ070C-PWR2	SRV - PCB ASSY POWER (R) 300T	WP-000306-00	OBS-MAIN PCB ASSEMBLY,,ISA300T,,(RIGHT CHANNEL)
PCB-QZ080C-PWR2	SRV - PCB ASSY, ISA 500 TI (R)	WP-000526-00	PCB ASSY,MAIN,ISA500TI,,BOTTOM
PCB-QZ090C-INP	SRV - PCB ASSY INPUT QZ090C	WP-007502-00	PCB ASSY,INPUT,ISA750/800TI,,
PCB-QZ090C-INP1	SRV - PCB ASSY INPUT QZ090C	WP-004508-00	PCB ASSY,DATAPORT,ISA450,,
PCB-QZ090C-PWR1	SRV - PCB ASSY POWER, ISA800T (L)	WP-000806-00	SRV-PCB ASSY,,ISA800T,,LT
PCB-QZ100C-PWR1	SRV - PCB ASSY POWER (R), RMX 1850 channel 1	WP-018503-00	PCB ASSY,PWR MOD,RT,RMX1850HD,,W/GAIN POTS
PCB-QZ100C-PWR2	SRV - PCB ASSY POWER (L), RMX 1850 channel 2	WP-018504-00	PCB ASSY,PWR MOD,LT,RMX1850HD,,
PCB-QZ110C-DIS	SRV - PCB ASSY, MAIN LED DISPLAY (W/GAIN POTS)	WP-004056-00	PCB ASSY,DISPLAY,RMX4050HD,,W/GAIN POTS
PCB-QZ110C-INP	SRV - PCB ASSY INPUT QZ110C	WP-004054-00	PCB ASSY,INPUT,RMX4050HD,,
PCB-QZ110C-LEDP	SRV - PCB ASSY, LED POWER DISPLAY	WP-004055-00	PCB ASSY,PWR LED,RMX4050HD,,
PCB-QZ110C-OUT	SRV - PCB ASSY OUTPUT QZ110C	WP-004058-00	PCB ASSY,OUTPUT,RMX-3RU,,
PCB-QZ110C-PSU	SRV - PCB ASSY POWER SUPPLY	WP-004052-00	PCB ASSY,AC,RMX4050HD,120V/240V,
PCB-QZ110C-PSU2	SRV - PCB ASSY RECTIFIER	WP-004057-00	PCB ASSY,RECT,RMX4050HD,,
PCB-QZ110C-PWR	SRV - PCB ASSY AMPLIFIER (RMX4050 HD)	WP-004061-00	PCB ASSY,,RMX4050HD,,
PCB-QZ111C-LF	SRV - PCB ASSY LINE FILTER	WP-004053-00	PCB ASSY,LINE FLTR,RMX4050HD/RMX5050,,
PCB-QZ120C-DIS	SRV - PCB ASSY DISPLAY QZ120C	WP-005056-00	PCB ASSY,DISPLAY/GAIN CONTROL,RMX4050/RMX5050,,
PCB-QZ120C-INP	SRV - PCB ASSY INPUT QZ120C	WP-005054-00	PCB ASSY,INPUT,RMX5050,,
PCB-QZ120C-LEDP	SRV - PCB ASSY POWER LED	WP-005055-00	PCB ASSY,PWR LED,RMX5050,,
PCB-QZ120C-PSU2	SRV - PCB ASSY RECTIFIER	WP-005057-00	PCB ASSY,RECT,RMX5050,,
PCB-QZ120C-PWR	SRV - PCB ASSY POWER QZ120C	WP-005052-00	PCB ASSY,,RMX5050,,
PCB-QZ130C-DIS	SRV - PCB ASSY DISPLAY QZ13XC	WP-001353-00	PCB ASSY,DISPLAY,ISA1350,,
PCB-QZ130C-INP	SRV - PCB ASSY INPUT QZ13XC	WP-001352-00	PCB ASSY,INPUT,ISA1350,,
PCB-QZ130C-INP1	SRV - PCB ASSY DATAPORT QZ13XC	WP-001356-00	PCB ASSY,DATAPORT,ISA1350,,
PCB-QZ130C-LEDP	SRV - PCB ASSY POWER LED	WP-001355-00	PCB ASSY,PWR LED,ISA1350,,
PCB-QZ130C-PSU2	SRV - PCB ASSY RECTIFIER	WP-001357-00	PCB ASSY,RECT,ISA1350,,
PCB-QZ130C-PWR	PCB ASSY., ISA 1350 CHANNEL MODULE	WP-001350-00	PCB ASSY,MAIN,ISA1350,,
PCB-R505011+LEDP	PCB ASSY,PWR LED,RMX5050,,	WP-005055-00	PCB ASSY,PWR LED,RMX5050,,
PCB-R85011+INP	PCB ASSY, INPUT, RMX850	WP-008509-00	PCB ASSY,INPUT,RMX850,,
PCB-R85011+PSU	PCB ASSY,AC PCB,RMX850/1450	WP-008502-00	PCB ASSY,AC PCB,RMX850/1450

Notes on Table 2

In Table 2, the fifth column—*Relationship*—describes how the new part number replaces the old one.

Superseded indicates that the old part is now obsolete and has been completely replaced by the new one; this could be due to lack of availability of the old part, a superior new part, etc.

Substitute means that the old part number is still in use, but the new part number may be used in its place. The new part might have better availabilty and pricing than the old one.

Related indicates that the new part may differ in superficial ways to the old one but still can be used instead. In some cases, a "related" new part may eventually supersede the old one.

Continued on next page ➜

Table 2. General QSC part updates

Original Part #	Description	New Part #	Description	Relationship
CA-015100-BD	SRV - OBS-15PF, 100V, 10%, DISK	CA-015001-10	SRV-15PF,10 PCNT,100V,CERAMIC NPO,DISC,	Substitute
CA-047002-30	47PF,5 PCNT,50V,CERAMIC NPO,0805,	CA-047005-GP	CC 50V 47PF 5% 0805	Substitute
CA-110100-BM	100PF,5 PCNT,100V,MICA,DIPPED,	CA-110001-10	100PF,5 PCNT,500V,MICA,DIPPED,	Substitute
CA-122005-GP	CC 50V 220pF 5% 0805 1.2X2.0	CA-122002-30	220PF,5 PCNT,50V,CERAMIC NPO,0805,	Substitute
CA-133500-CM	SRV-330PF,5 PCNT,500V,MICA,DIPPED,NON-AI	CA-133001-10	330PF,5 PCNT,500V,MICA,DIPPED,	Substitute
CA-210050-CP	SRV-0.001UF,5 PCNT,50V,FILM,DIPPED,	CA-210002-10	0.001UF,5 PCNT,100V,FILM,DIPPED,	Substitute
CA-210100-BP	SRV - .001UF, 100V, 10%, MYLAR	CA-210002-10	0.001UF,5 PCNT,100V,FILM,DIPPED,	Substitute
CA-215100-BP	0.0015UF,10 PCNT,100V,FILM,DIPPED,	CA-215002-10	0.0015UF,5 PCNT,200V,FILM,DIPPED,	Substitute
CA-215200-BP	SRV - .0015UF, 200V, 10%, MYLAR	CA-215002-10	0.0015UF,5 PCNT,200V,FILM,DIPPED,	Substitute
CA-222017-GP	2200PF,10 PCNT,50V,CC,0805,	CA-222005-30	0.0022UF,5 PCNT,50V,CERAMIC NPO,0805,	Substitute
CA-222050-CP	OBS-0.0022UF,5 PCNT,50V,FILM,DIPPED,NON-AI	CA-222001-10	0.0022UF,5 PCNT,50V,FILM,DIPPED,	Substitute
CA-222200-BP	SRV-0.0022UF,10 PCNT,200V,FILM,DIPPED,NON-AI	CA-222002-10	0.0022UF,10 PCNT,200V,FILM,DIPPED,	Substitute
CA-233100-BP	SRV - OBSOLETE- .0033UF, 100V, 10%, MYLAR	CA-233001-10	0.0033UF,10 PCNT,100V,FILM,DIPPED,	Substitute
CA-268100-CP	SRV - .0068UF, 100V, 5%, MYLAR	CA-268001-10	SRV-0.0068UF,5 PCNT,100V,FILM,DIPPED,	Substitute
CA-310100-BP	SRV - .01UF, 100V, 10%, MYLAR	CA-310001-10	0.01UF,10 PCNT,100V,FILM,DIPPED,	Substitute
CA-368050-CP	SRV-0.068UF,5 PCNT,50V,FILM,DIPPED,	CA-368006-GP	.068UF,5 PCNT,50V,FILM,,	Substitute
CA-368100-BP	OBSOLETE - .068UF, 100V, 10%, MYLAR	CA-368001-10	SRV-0.068UF,5 PCNT,100V,FILM,DIPPED,	Substitute
CA-410008-30	SRV - .1UF 50V 10% CER X7R SM	CA-410006-30	0.1UF,10 PCNT,50V,CERAMIC X7R,1206,	Substitute
CA-410013-GP	CER 2 1206 10% 50V .1UF	CA-410006-30	0.1UF,10 PCNT,50V,CERAMIC X7R,1206,	Substitute
CA-410100-BP	SRV-0.1UF,10 PCNT,100V,FILM,DIPPED,	CA-410002-10	0.1UF,5 PCNT,100V,FILM,DIPPED,	Substitute
CA-410100-CP	SRV-0.1UF,5 PCNT,100V,FILM,DIPPED,NON-AI	CA-410002-10	0.1UF,5 PCNT,100V,FILM,DIPPED,	Substitute
CA-412100-CP	SRV - .12UF, 100V, 5%, MYLAR	CA-412001-10	SRV-0.12UF,5 PCNT,100V,FILM,DIPPED,	Substitute
CA-422001-00	0.22UF,20 PCNT,250VAC,FILM,DIPPED,XCAP	CA-422005-GP	CM 250V .22UF 10% RL	Related
CA-610035-BE	SRV - 10UF, 35V, ELEC., RADIAL	CA-610002-10	10UF,20 PCNT,35V,ELECTROLYTIC,,	Substitute
CA-647000-GP	OBS-47UF 16V NON POLAR 20% ELECTROLYTIC RL	CA-647006-GP	CE 16NP 47UF 20% RL	Superseded
CA-647004-10	OBS-47UF,20 PCNT,50V,ELECTROLYTIC,,	CA-647002-10	47UF,20 PCNT,50V,ELECTROLYTIC,,LOW PROFILE	Superseded
CA-647010-BN	SRV - 47UF, 10V, 10% RADIAL, NON-POLAR CAP LYTIC	CA-647001-10	47UF,10 PCNT,10V,ELECTROLYTIC,,NON-POLAR	Substitute
CA-647050-BE	SRV - 47UF, 50V, ELECT., RADIAL	CA-647002-10	47UF,20 PCNT,50V,ELECTROLYTIC,,LOW PROFILE	Substitute
CA-722002-10	220UF,20 PCNT,25V,ELECTROLYTIC,,	CA-722006-GP	CE 25V 220UF 20% RL	Substitute
CA-722010-BN	SRV - 220UF 10V CAPACITOR	CA-722001-10	220UF,20 PCNT,10V,ELECTROLYTIC,,NON-POLAR	Substitute
CA-722025-BE	SRV - 220UF, 25V, ELECT., RADIA	CA-722002-10	220UF,20 PCNT,25V,ELECTROLYTIC,,	Substitute
CA-747009-GP	470UF,20%,16V,CE,,RLT	CA-747001-10	470UF,20 PCNT,16V,ELECTROLYTIC,,	Substitute
CH-000042-00	3" REAR RACK EAR FAB	CH-000301-GP	REAR RACK EAR, 3IN. UNIVERSAL	Substitute
CH-000215-01	GRILLE,,,AD-S82, BLACK,	PA-000136-GP	GRILLE ASSEMBLY,AD-S82,I-82H, BLACK,WITH LOGO	Superseded
CH-000215-01	GRILLE,,,AD-S82, BLACK,	PA-000136-GP	GRILLE ASSEMBLY,AD-S82,I-82H, BLACK,WITH LOGO	Related
CH-000215-02	GRILLE, AD-S82, WHITE	PA-000137-GP	GRILLE ASSEMBLY,AD-S82,WHITE,WITH LOGO	Superseded
CH-000309-GP	OBS-OUTPUT BRACKET	PA-000043-00	PLATE ASSY,PLX/RMX,OUTPUT,,	Superseded
CH-000359-01	SRV - GRILLE	PA-000136-GP	GRILLE ASSEMBLY,AD-S82,I-82H, BLACK,WITH LOGO	Related
CH-000386-01	GRILLE,,I-282H/AD-S282,BLACK	PA-000134-GP	GRILLE ASSEMBLY,AD-S282,BLACK,WITH LOGO	Superseded
CH-000386-02	GRILLE,,,I-282H/AD-S282,WHITE	PA-000135-GP	GRILLE ASSEMBLY,AD-S282,WHITE,WITH LOGO	Superseded
CH-000442-GP	SRV-BRACKET,YOKE,CINEMA,YM-360,	CH-000805-GP	BRACKET,YOKE,CINEMA,YM-46,	Superseded
CH-000492-GP	SIDE HANDLE BACK,,,HPR,	CH-000523-GP	HANDLE BAR,FOR HPR/KW 151/181/152/153,SIDE HANDLE,,	Superseded
CH-000793-GP	GRILLE,,,AD-C81Tw,	PA-000160-GP	GRILL ASSEMBLY,AD-C81Tw ,,,,	Related
CH-000809-00	OBS-CHASSIS,MAIN,,GX SERIES,	CH-000873-00	CHASSIS,MAIN,,GX SERIES,2MM THICK STEEL	Superseded
CH-000816-GP	GRILLE,BLACK,,AD-S32T,	PA-000166-GP	GRILLE ASSEMBLY,AD-S32T,BLACK,	Superseded
CH-000993-TS	OBS-INPUT/OUTPUT PLATE,(BARE),,HPR122i,	CH-000545-GP	PANEL,INPUT,,HPR122i,	Superseded
CH-000994-TS	OBS-INPUT/OUTPUT PLATE,(BARE),,HPR152i,	CH-000546-GP	PANEL,INPUT,,HPR152i,	Superseded
CH-000995-TS	OBS-INPUT/OUTPUT PLATE,(BARE),,HPR153i,	CH-000547-GP	PANEL,INPUT,,HPR153i,	Superseded
CH-000996-TS	OBS-INPUT/OUTPUT PLATE,(BARE),,HPR151i,	CH-000548-GP	PANEL,INPUT,,HPR151i,	Superseded
CH-000997-TS	OBS-INPUT/OUTPUT PLATE,(BARE),,HPR181i,	CH-000549-GP	PANEL,INPUT,,HPR181i,	Related
CH-004112-00	OBS-PANEL,INPUT,LOWER,MXA,	WP-001522-01	SRV-LOWER INPUT CARD,MXA SERIES, 1000A/ MX1500A/2000A/3000A,,	Related
CH-140210-BX	SRV - 1400 KNOB FABRICATION	PL-000178-00	SRV-KNOB,,1400,PLASTIC,BLACK,	Substitute
CO-000075-00	SRV - XLRF COMBO RT	CO-000167-00	SRV-CONN XLR COMBO,,,,	Substitute
CO-000077-00	SVC OBS - PLUG EURO 7	CO-000100-00	SVC PH OUT- CONN. PLUG 7 PIN EURO BLK.	Substitute
CO-000086-00	SRV - XLR COMBO CONNECTOR	CO-000168-00	SOB-XLR,COMBO,3 POS,FEMALE,VERTICAL	Substitute
CO-000111-00	SRV - CONN PLUG 3-PIN EUR	CO-000198-00	PLUG,EURO3 POS,MALE,GREEN, WITH STRAIN RELIEF	Substitute
CO-000137-00	SRV - CONN PLUG 3-PIN EURO STRAIN RELIEF	CO-000198-00	PLUG,EURO3 POS,MALE,GREEN, WITH STRAIN RELIEF	Substitute
CO-000162-00	SRV - BNDG POST A, DUAL S'	PA-000043-00	PLATE ASSY,PLX/RMX,OUTPUT,,	Substitute

Continued on next page ➜

Table 2, continued. General QSC part updates

Original Part #	Description	New Part #	Description	Relationship
CO-000163-00	SRV - BNDG POST B, DUAL S	PA-000043-00	PLATE ASSY,PLX/RMX,OUTPUT,,	Substitute
CO-000200-00	OBS-PLUG,EURO POWER,8 POS,MALE,GREEN	CO-000447-00	PLUG,EURO POWER,8 POS,MALE,GREEN HIGH CURRENT	Superseded
CO-000220-GP	CONN HD15	CO-000106-00	JACK,HD15,15 POS,FEMALE,RIGHT ANGLE SWAGED JACK SCREW	Substitute
CO-000228-GP	EURO 3 PIN CONNECTOR, GREEN	CO-000436-00	PLUG,EURO,3 POS,MALE,GRN	Substitute
CO-000228-GP	EURO 3 PIN CONNECTOR, GREEN	CO-000198-00	PLUG,EURO3 POS,MALE,GREEN, WITH STRAIN RELIEF	Related
CO-000237-GP	SRV-4 POLE SPKR TERMINAL	PA-000043-00	PLATE ASSY,PLX/RMX,OUTPUT,,	Superseded
CO-000357-GP	IEC CONNECTOR,20A,3 POS,FEMALE,	CO-000309-GP	AC INLET,125/250V,20A	Substitute
CO-000360-GP	INLET CONNECTOR,AC IEC LATCHING, 15A,,,	CO-000386-00	JACK,IEC,3 POS,FEMALE,LOCKING	Superseded
CO-300112-PJ	JACK,PHONE,3 POS,FEMALE,	CO-000235-GP	PHONE JACK 06.4	Related
IC-000008-00	SRV - SMT MODULE, POS. STEP DRIVER	WP-000008-00	SOB-PCB ASSY,POS STEP DRVR,EX/MX/PL SERIES,,SMT	Substitute
IC-000009-00	SRV - SMT MODULE, NEG. STEP DRIVER	WP-000009-00	SOB-PCB ASSY,NEG STEP DRVR,EX/MX/PL SERIES,,SMT	Substitute
IC-000071-GP	OBS-IC LM7915CT,REGULATOR,,,	IC-000378-GP	IC LM7915CT,REGULATOR,-15V,,	Superseded
IC-000072-GP	IC,LM7815CT REGULATOR,,,	IC-000379-GP	IC LM7815CT,REGULATOR,15V,,	Superseded
IC-000073-30	TRANSCONDUCTANCE OPAMP,DUAL,LM13600M,,	IC-000212-GP	IC LM13700M	Substitute
IC-000075-GP	IC VOLTAGE REG,+5,LM78L05,SMT,	IC-000128-30	VOLTAGE REGULATOR,+5V,LM78L05,,	Substitute
IC-000076-GP	IC LM339,SMD COMPARATORS,,,	IC-000054-30	COMPARATOR,QUAD,LM339AM,SMT,	Substitute
IC-000079-GP	IC MC33078,OP-AMP,,SMT,	IC-000048-30	OPAMP,DUAL,MC33078,,	Substitute
IC-000133-30	COMPARATOR,SINGLE,LM311,SMT,	IC-000214-GP	LM311M VOLTAGE	Substitute
IC-000212-GP	IC LM13700M	IC-000470-30	TRANSCONDUCTANCE OPAMP,DUAL,LM13700,SMT,	Substitute
IC-000377-GP	IC 7805,REGULATOR,5V,,	IC-000042-00	VOLTAGE REGULATOR,+5V,MC7805CT,,	Substitute
IC-000378-GP	IC LM7915CT,REGULATOR,-15V,,	IC-000230-00	VOLTAGE REGULATOR,-15V,LM7915CT,,	Substitute
IC-000379-GP	IC LM7815CT,REGULATOR,15V,,	IC-000229-00	VOLTAGE REGULATOR,+15V,LM7815CT,,	Substitute
IC-000380-GP	IC TL072,OPAMP,DUAL,SO-8,	IC-000072-OP	SRV-OPAMP,DUAL,TL072,,	Substitute
IC-000381-GP	IC TL074CD-SO14,OPAMP,QUAD,SO-14,	IC-000150-30	OPAMP,QUAD,TL074,SMT,	Substitute
IC-005532-AC	SRV - OP AMP NE5532 (PHILLIPS)	IC-000211-GP	IC NE5532 OP AMP	Substitute
IC-005532-OP	OPAMP,DUAL,NE5532,,	IC-000211-GP	IC NE5532 OP AMP	Substitute
LB-000054-00	OBS-WARNING,SHOCK CAUTION,TOP,,	LB-000354-GP	LABEL,TOP COVER, WARNING	Substitute
LB-070224-00	SRV-PRODUCT,OUTPUT,REAR,MX700,	LB-070222-00	SRV-PRODUCT,FACEPLATE,,MX700,	Substitute
MS-000049-00	SRV - 4.7" 24V DC FAN	MS-000087-00	SOB-FAN,24VDC,4.7",,BLACK HUB	Superseded
MS-000052-00	SRV - 3.5" FAN, 24 VDC	MS-000085-00	FAN,24VDC,3.15",,	Substitute
MS-000091-00	SRV - FAN 5VDC 1.58"	MS-000116-00	SRV-FAN,RAVE SERIES,5VDC,1.58",,	Substitute
MS-000141-GP	OBS-FUSE T12A/250V 6.3X32MM	MS-000124-GP	FUSE 12A 250V 6.3 X 32MM	Superseded
MS-000291-GP	OBS-CD FOR QSC,,HPRi SERIES,,,	RM-000008-GP	CD,OWNERS MANUAL,QUICK START GUIDE,,HPRi SERIES,	Superseded
MS-120250-FU	SRV-FUSE,12A,250V,,	MS-000124-GP	FUSE 12A 250V 6.3 X 32MM	Substitute
PA-000132-00	SRV-INPUT ASSY,WL3082,,,	PA-000197-00	INPUT PLATE ASSY,DUAL NL-8,,,	Superseded
PA-000193-GP	GRILLE ASSEMBLY,AD-S52,BLACK,WITH LOGO,,	CH-000361-01	GRILLE,,BLACK,AD-S52,	Substitute
PA-000194-GP	GRILLE ASSY,AD-S52,WHT,W/LOGO,,	CH-000361-02	GRILLE,,WHITE,AD-S52,	Substitute
PA-000219-TS	GRILLE ASSY KIT,AD-S28Tw,,,	WP-000289-00	ASSEMBLY,GRILLE,AD-S28Tw,,	Superseded
PC-DDI110-TS	PCB,DDI-11,,	PC-000515-TS	PCB,BARE,DDI-11,,,	Superseded
PL-000026-PL	SRV - TO-220 TEK-SIL INSULATOR	PL-000154-GP	INSULATION SHEET IC ISA	Substitute
PL-000073-GP	PLUG ENDCAP,FOR HPR 3WAY,,,,	PL-000473-GP	SRV-PLUG ENDCAP,FOR HPR 3WAY,,,,	Related
PL-000075-GP	CABLE TIE,2.5X120MM,KFB101,,,	PL-000074-00	TIE WRAP,,8x.01",NYLON,BLACK,	Substitute
PL-000096-00	SRV - INSULATOR,FAN DUCT,PLX	PL-000144-00	INSULATOR,FAN DUCT,PLC,FISH PAPER,,	Substitute
PL-000157-GP	XFMR RUBBER PAD BLACK	PL-000573-00	PAD,TRANSFORMER,,FOAM,,GX SERIES	Superseded
PL-000307-00	KNOB,MALE,M5X0.8,,,	PL-000307-01	KNOB,M5x.8,MALE,I-282 YOKE,,,,	Superseded
PL-000380-00	SRV-GASKET,MOUNTING,PM-1000,PVC,BLACK,	PS-000128-00	GASKET,1/8" THICK X 1/2" WIDE (50ft ROLL),CLOSED CELL FOAM,	Superseded
PL-000446-GP	HORN,W/GASKET,HF,HPR152F/HPRI52I,,,	PL-000723-TS	ASSEMBLY,HF HORN,W/GASKET,HPR152i,,,	Superseded
PL-000516-01	CLIP,CHRISTMAS TREE,.187,,BLACK,AD-S52	PL-000066-00	CLIP,CHRISTMAS TREE,,NYLON,BLACK,	Related
PL-000558-GP	GRILLE RETAINING PIN,,AD-S32,PLASTIC,,(TXMAS TREES FOR GRILLE)	PL-000562-GP	GRILLE PIN,AD-S32T,,,BLACK,	Superseded
PL-000601-01	PLATE,POLE CUP,DUAL ANGLE,K10,,BLK,	SG-000562-TS	ASSEMBLY,POLE CUP,DUAL ANGLE,K10,,BLK,	Related
PL-000612-GP	OBS-FEET A,,,,,	PL-000512-GP	FOOT A,,,,,	Superseded
PL-000721-TS	OBS-ASSEMBLY,HORN,HPR122i,,,	PL-000722-TS	ASSEMBLY,HF HORN,W/GASKET,HPR122i,,,	Superseded
PL-000723-TS	ASSEMBLY,HF HORN,W/GASKET,HPR152i,,,	PL-000446-GP	HORN,W/GASKET,HF,HPR152F/HPRI52I,,,	Substitute
PT-000003-TS	GAIN POTENTIOMETERS,2.5K,,,NON-DETENT,	PT-225001-GP	GAIN 2.5K 20% .1W RT ANG SHAFT	Superseded
QD-000004-TX	SRV-TRANSISTOR NPN,60V,0.5A,1W,MPSW05,TO226AE,	QD-000211-GP	TR MPS A06VCE 80V NS	Substitute
QD-000005-QD	SRV - C2336 NPN NEC TRANS. TO-220	QD-000077-00	TRANSISTOR PNP,250V,8A,50W,MJE15033,TO-220,	Substitute

Continued on next page ➜

Table 2, continued. General QSC part updates

Original Part #	Description	New Part #	Description	Relationship
QD-000006-QD	SRV - A1006 PNP NEC TRANS. T0-220	QD-000076-00	TRANSISTOR NPN,250V,8A,50W,MJE15032,TO-220,	Substitute
QD-000013-00	SRV-MOSFET N-CHANNEL,60V,50A,150W,MTP52N06V,TO-220,	QD-000031-QD	MOSFET N-CHANNEL,60V,50A,150W,MTP45N06,TO-220,	Substitute
QD-000013-01	SRV-MOSFET N-CHANNEL,60V,50A,150W,STP50N06L,TO-220,	QD-000031-QD	MOSFET N-CHANNEL,60V,50A,150W,MTP45N06,TO-220,	Substitute
QD-000013-QD	SRV - N-FET SWITCH, 60V, 52 AMP	QD-000031-QD	MOSFET N-CHANNEL,60V,50A,150W,MTP45N06,TO-220,	Substitute
QD-000014-QD	DIODE RECTIFIER ULTRAFAST,200V,15A,,MUR1520,TO-220,35NS	QD-000215-GP	DIODE MUR1520 15A 200V	Substitute
QD-000017-QD	SRV - MPSA93 TRANSISTOR PNP 200V	QD-000169-00	IGBT,600V,55A,200W,IRG4PC50U,TO-247,	Substitute
QD-000031-QD	MOSFET N-CHANNEL,60V,50A,150W,MTP45N06,TO-220,	QD-000260-GP	MOSFET,N-CH,60V,52A,52N06V	Substitute
QD-000031-QD	MOSFET N-CHANNEL,60V,50A,150W,MTP45N06,TO-220,	QD-000222-GP	SRV-TR RFP50N06 N-CH PWR	Substitute
QD-000040-00	SRV-BRIDGE RECTIFIER,400V,35A,,,,IN-LINE	QD-000165-00	BRIDGE RECTIFIER,,,,SDB4004,,400V 40A	Substitute
QD-000043-00	SRV - IGBT 600V 55A 200W IRGPC50U	QD-000169-00	IGBT,600V,55A,200W,IRG4PC50U,TO-247,	Superseded
QD-000055-10	SRV-TRANSISTOR NPN,80V,0.25A,1.5W,2N4410,TO-92,	QD-004410-TX	SRV - BJTN 80V .25A 1.5W 2N4410	Substitute
QD-000060-00	SRV - IGBT 600V 40A 160W IRGPC40U	QD-000162-00	IGBT,600V,40A,160W,IRG4PC40U,TO-247,	Superseded
QD-000060-00	SRV - IGBT 600V 40A 160W IRGPC40U	QD-000162-00	IGBT,600V,40A,160W,IRG4PC40U,TO-247,	Substitute
QD-000061-00	OBS - IGBT 600V 60A 200W IXGH1644	QD-000169-00	IGBT,600V,55A,200W,IRG4PC50U,TO-247,	Superseded
QD-000073-00	SRV - XISTOR IGBT 59A 450V	QD-000169-00	IGBT,600V,55A,200W,IRG4PC50U,TO-247,	Superseded
QD-000076-00	TRANSISTOR NPN,250V,8A,50W,MJE15032,TO-220,	QD-000207-GP	XISTOR NPN 250V 0.5A MJE15032	Substitute
QD-000077-00	TRANSISTOR PNP,250V,8A,50W,MJE15033,TO-220,	QD-000210-GP	XISTOR PNP 250V MJE15033	Substitute
QD-000092-00	TRANSISTOR NPN,100V,3A,40W,TIP31C,TO-220,	QD-000214-GP	TR TIP31C SAMSUNG	Substitute
QD-000103-30	TRANSISTOR NPN,40V,0.2A,0.2W,MMST3904,SOT-23,	QD-000204-GP	XISTOR NPN 60V 200MA 3904 SOT-23	Substitute
QD-000104-30	TRANSISTOR PNP,40V,0.2A,0.2W,MMST3906,SOT-23,	QD-000205-GP	XISTOR PNP 40V 0.2A TR3906 SOT-23	Substitute
QD-000105-30	TRANSISTOR NPN,300V,0.2A,0.2W,MMBTA42,SOT-23,	QD-000213-GP	TR KST42	Substitute
QD-000166-00	SRV-BRIDGE RECTIFIER,400V,35A,,,,PLASTIC CASE	QD-400400-BX	SRV-BRIDGE RECTIFIER,400V,35A,,,,PLASTIC OR METAL CASE	Substitute
QD-000188-00	OBS-MOSFET N-CHANNEL,500V,55A,600W,IXFN55N50,SOT-227B,	SR-000120-00	FET, IXYS, IXFN60N60	Superseded
QD-000208-GP	XISTOR PNP 230V 15A 2SA1943	QD-001943-PN	TRANSISTOR PNP,230V,15A,150W,2SA1943-R,TO-264,	Substitute
QD-000209-GP	XISTOR NPN 230V 15A 2SC5200	QD-005200-NP	TRANSISTOR NPN,230V,15A,150W,2SC5200,TO-264,	Substitute
QD-000221-GP	SRV-TRIAC 600V 40A MAC224 A8	SG-000522-00	RMX TRIAC ADAPTER, (SR-000117-00 WITH TRIAC 8910-0599-0)	Substitute
QD-000223-GP	TR 2N5064 TRIODE	QD-000216-GP	THYRISTOR 200V 0.1W 2N5064	Superseded
QD-000260-GP	MOSFET,N-CH,60V,52A,52N06V	QD-000222-GP	SRV-TR RFP50N06 N-CH PWR	Substitute
QD-000274-GP	SRV-TRANSISTOR NPN,40V,0.5A,0.2W,2SD0602A,SOT-23,	QD-000339-GP	TRANSISTOR, NPN,40V,0.5A,0.2W,2SC3325,SOT-23,	Substitute
QD-000275-GP	SRV-TRANSISTOR PNP,40V,0.5A,0.2W,2SB0710A,SOT-23,	QD-000340-GP	TRANSISTOR, PNP,40V,.5A,.2W,2SA1313,SOT-23,	Substitute
QD-000308-GP	TR MMBTA42 NPN SMD,,,,,SOT-23,	QD-000105-30	TRANSISTOR NPN,300V,0.2A,0.2W,MMBTA42,SOT-23,	Substitute
QD-000341-TS	XISTOR PNP 230V 15A 2SA1943	QD-000208-GP	XISTOR PNP 230V 15A 2SA1943	Superseded
QD-000342-TS	XISTOR NPN 230V 15A 2SC5200	QD-000209-GP	XISTOR NPN 230V 15A 2SC5200	Superseded
QD-000347-GP	FETN,60V,50A,150W,,,	QD-000260-GP	MOSFET,N-CH,60V,52A,52N06V	Superseded
QD-000348-00	SRV-IGBT,600V,75A,200W,IXGR50N60C2,TO-247,	QD-000315-00	IGBT,600V,75A,250W,IXGR60N60C2,TO-247,	Superseded
QD-000424-TX	SRV - 2SD424 XSTOR NPN TO-3/TO-204AA	QD-000032-QD	SRV-TRANSISTOR NPN,200V,16A,250W,MJ15022,TO-3,	Substitute
QD-000914-DX	SRV - DIOD 75V .075A 4NS 1N914	QD-004148-DX	DIODE,75V,0.075A,,1N4148,DO-35,4NS	Superseded
QD-001302-PN	SRV-TRANSISTOR PNP,200V,15A,150W,2SA1302,TO-264,	QD-001943-PN	TRANSISTOR PNP,230V,15A,150W,2SA1943-R,TO-264,	Superseded
QD-001340-LR	SRV-LED,,,,RED,,VOLTAGE REFERENCE	QD-000134-LR	SOB-LED,,,,RED,,NA	Substitute
QD-002762-TM	OBS-170V -200V, 2A TO-220, NPN	QD-000076-00	TRANSISTOR NPN,250V,8A,50W,MJE15032,TO-220,	Superseded
QD-002763-TM	OBS-170-220V, 2A, TO-220, PNP	QD-000077-00	TRANSISTOR PNP,250V,8A,50W,MJE15033,TO-220,	Superseded
QD-002763-TU	SRV - MJ15031 TRANSISTOR PNP TO-220	QD-000077-00	TRANSISTOR PNP,250V,8A,50W,MJE15033,TO-220,	Substitute
QD-003281-NP	SRV-TRANSISTOR NPN,200V,15A,150W,2SC3281,TO-264,	QD-005200-NP	TRANSISTOR NPN,230V,15A,150W,2SC5200,TO-264,	Superseded
QD-003906-TX	SRV - BJTP 40V .2A 1.5W 2N3906	QD-000063-10	TRANSISTOR PNP,40V,0.2A,1.5W,2N3906,TO-92,	Superseded
QD-004004-DX	DIODE,400V,1A,,1N4004,DO-41,2US	QD-000202-GP	DIODE 1N4004 AL	Substitute
QD-004004-DX	DIODE,400V,1A,,1N4004,DO-41,2US	QD-004004-VP	DIODE,400V,1A,,1N4004,DO-41 HAIRPIN,2US	Substitute
QD-004934-DX	DIODE,100V,1A,,1N4934,DO-41,200NS	QD-000206-GP	DIOD RECT FAST, IN4934 AT	Substitute
QD-004934-VP	OBS-DIODE RECT DO41 FAST 100V 1AVP	QD-004934-DX	DIODE,100V,1A,,1N4934,DO-41,200NS	Related
QD-008599-TX	SRV - BJTP 60V .5A .625W MPS8599	QD-000056-10	SRV-TRANSISTOR PNP,60V,0.5A,0.625W,MPS8599,TO-92,	Superseded
QD-250400-BX	SRV - 25A 400V BRIDGE RECTIFIER	QD-400400-BX	SRV-BRIDGE RECTIFIER,400V,35A,,,,PLASTIC OR METAL CASE	Substitute
RE-.01002-GP	0.1R,5 PCNT,2W,RMF,ATS METAL,	RE-.01001-10	0.1,5 PCNT,2W,METAL OXIDE FP,MINI,	Substitute
RE-.02201-GP	0.22 OHM 5% 3W THK FLM	RE-.02202-GP	0.22 5% 3W THICK FILM	Superseded
RE-.56005-EM	SRV-5.6,5 PCNT,2W,METAL OXIDE FP,,	RE-.56006-GP	RMF 2W 5.6 OHM 5%	Substitute
RE-000006-VP	SOB-PTC,100 OHMS,470 OHMS,,60C,VERTICAL	RE-000006-PT	PTC,100 OHMS,470 OHMS,,60C,	Substitute
RE-000160-NR	SRV-SG-160 NTC RESISTOR	RE-000160-NT	SRV-NTC,2.5 OHMS,15 AMPS,,,INRUSH LIMIT	Substitute
RE-004751-BM	SOB-47.5,1 PCNT,1/4W,METAL FILM,,	RE-004751-10	47.5,1 PCNT,1/3W,METAL FILM,,	Substitute

Continued on next page ➜

Table 2, continued. General QSC part updates

Original Part #	Description	New Part #	Description	Relationship
RE-004753-GP	RMG 1/10W 47.5 OHM 1% 0805	RE-004752-30	47.5,1 PCNT,1/10W,THICK FILM,0805,100V	Substitute
RE-010009-GP	OBS-100 OHM POT PCB MOUNT	PT-110002-GP	TRIM POT,100 OHM,20 PCNT,0.15W,,	Superseded
RE-04001-00	SRV - RESISTOR PWR FILM TO220 .04 1% 20W	RE-.04001-00	SRV-0.04,1 PCNT,20W,MICRONOX FILM,TO-220,	Superseded
RE-068005-EM	SRV - 680 OHM,2 W,MET OX,5%,RESISTOR	RE-068002-00	680,5 PCNT,2W,METAL OXIDE FP,,	Substitute
RE-082001-10	SRV-820,5 PCNT,2W,METAL OXIDE FP,MINI,	RE-082002-00	820,5 PCNT,2W,METAL OXIDE FP,,	Related
RE-082003-GP	RMG 1/8W 820 OHM 5% 1206	RE-082008-GP	820 1% 1/8W THK FLM 1206 200V	Substitute
RE-082006-GP	OBS-RMG 5% 820 OHM 1/10W 0805	RE-082004-GP	820 OHM,5 PCNT,1/10W,RMG,0805,	Superseded
RE-120009-GP	OBS-2.0K,1 PCNT,1/10W,THICK FLM,0805,100V	RE-120004-GP	RMG 1/10W 2K 1% 0805	Superseded
RE-125005-HW	SRV - 2.5K OHM, 5W, WIREWOUND 10%	RE-124001-00	SRV - 2.4K 2W 5% MOFP	Substitute
RE-136001-00	SRV-3.6K,5 PCNT,5W,METAL OXIDE FP,,	RE-135005-HW	SRV - 3.5K 5W 5% WW	Substitute
RE-139002-10	SRV - RES MOFP 3.9K 5% 2W	RE-139003-00	3.9K,5 PCNT,2W,METAL OXIDE FP,,	Related
RE-175005-BC	OBS-7.5K 1/4W 5% CF	RE-175001-BM	SRV-7.50K,1 PCNT,1/4W,METAL FILM,,	Superseded
RE-210003-30	10.0K,1 PCNT,1/10W,THICK FILM,0805,100V	RE-210007-GP	10K 1% 1/10W THK FLM 0805	Substitute
RE-210006-GP	RMG 1/10W 10K 5% 0805	RE-210007-GP	10K 1% 1/10W THK FLM 0805	Substitute
RE-210006-GP	RMG 1/10W 10K 5% 0805	RE-210003-30	10.0K,1 PCNT,1/10W,THICK FILM,0805,100V	Substitute
RE-213005-GP	13K,1 PCNT,1/10W,RMG,0805,	RE-213004-30	SRV-13.0K,1 PCNT,1/10W,THICK FILM,0805,100V	Substitute
RE-215004-00	15K,5 PCNT,2W,METAL OXIDE FP,,	RE-215006-GP	RMF 2W 15K 5% AL METAL	Substitute
RE-218701-GP	OBS-18.7K,1 PCNT,1/10W,RMG,0805,	RE-218702-GP	18.7K,1 PCNT,1/10W,THICK FILM,0805,	Superseded
RE-247002-DM	SRV - 47K 1W 2% RESISTOR	RE-247005-DM	47K,5 PCNT,1W,METAL OXIDE FP,,	Substitute
RE-247005-GP	OBS-RMG 1/10W 47K 5% 0805	RE-247006-GP	47K 1% 1/10W THK FLM 0805 100V	Superseded
RE-56002-10	SRV - RESISTOR MOFP 5.6 5% 2W MINI	RE-.56002-10	5.6,5 PCNT,2W,METAL OXIDE FP,MINI,	Superseded
SC-000085-GP	SELF SCREW,3X8, WITH,SERRATED HEAD,,,	SC-000046-GP	SCREW,M3 X 8MM SELF TAPPING	Substitute
SC-040008-GP	P/P,M4,10MM,BLK,TRIANGULAR TIP	SC-000205-00	SCR,PHH,PNH SERR BSE,MACH,TAPTITE TYPE B0,,,M4,10 L,STL,BLK,ZINC CR3,	Substitute
SC-063061-PP	SRV - #6-32 X 3/8" "F" P/P BLACK	SC-060061-PP	,PHILLIPS,PANHEAD,,,,,#6-32,0.375" L,,,BLACK,CR3	Substitute
SC-082060-PP	,PHILLIPS,PANHEAD,,,,,#8-18,0.375" L TYPE B THREAD,,,ZINC PLATED,TYPE 1,CR3	SC-000017-00	SCREW,TAP,PH,M4.2 X 1.4 X 10MM	Substitute
SG-000300-00	SRV - DSP-3 EXT. POWER SUPPLY	FG-000306-00	ACCESSORY,DPX-1,,,DSP-3	Substitute
SG-000503-00	DDI-5 DATAPORT ADAPTER	CO-000003-AC	SRV - HD15 DATAPORT F/F ADAPTER	Substitute
SG-000509-00	OBS-MXA LOWER INPUT CARD	WP-001522-01	SRV-LOWER INPUT CARD,MXA SERIES, 1000A/ MX1500A/2000A/3000A,,	Substitute
SG-000512-00	DDI-8, 2-CHANNEL INPUT ROUTER MODULE	SG-000523-00	DDI-8C,2 CHANNEL INPUT ROUTER MODULE,,	Superseded
SG-000557-TS	GRILLE ASSY WITH LOGO,,K8,	PA-000246-01	GRILLE ASSY,K12 WITH LOGO,BLK,,,	Related
SG-000557-TS	GRILLE ASSY WITH LOGO,,K8,	PA-000244-01	GRILLE ASSY,K8 WITH LOGO,BLK,,,	Superseded
SG-000561-TS	GRILLE ASSY WITH LOGO,,K10,	PA-000245-01	GRILLE ASSY,K10 WITH LOGO,BLK,,,	Superseded
SG-000565-TS	GRILLE ASSY WITH LOGO,,K12,	PA-000246-01	GRILLE ASSY,K12 WITH LOGO,BLK,,,	Related
SP-000008-00	SRV-WOOFER,8",FIBERGLASS,FERRITE,AUDAX AP210,	SP-000067-00	WOOFER,8",8 OHM,,CELESTION,QSC8FG,(AD-S82)	Substitute
SP-000009-00	OBS-WOOFER,8",PAPER,NEO,B&C 8NX-8,	SP-000109-00	WOOFER,8",NEO,,B&C 8NX-8,8ohm,(AD-S82H)	Substitute
SP-000010-00	SRV-TWEETER,1.0",TITANIUM DOME,NEO,AUDAX TH025,WAVEGUIDE	SP-000061-00	TWEETER,1",,,ZYLUX,AD-S52/82	Substitute
SP-000021-00	OBS-COMPRESSION DRIVER,1.0",MYLAR,FERRITE,B&C,DE10, 8ohm	SP-000110-00	DRIVER,HF COMPRESSION,,,B&C DE-10,8ohm	Substitute
SP-000027-00	SVC PH OUT-TWEETER,1",TITANIUM DOME,DOUBLE NEO,AUDAX,CEILING SPEAKER	SP-000062-00	TWEETER,1",4 OHMS,TITANIUM, NEO,ZYLUX,AD-C52	Substitute
SP-000028-00	PHASE OUT-WOOFER,5 1/4",FIBERGLASS CONE,FERRITE,AUDAX HP130FG,CEILING SPEAKER	SP-000059-00	WOOFER,5.25",8 OHMS,FIBERGLASS CONE,FERRITE,ZYLUX,AD-C52	Superseded
SP-000031-00	WAVEGUIDE,90 X 60,1" THROAT,HIPS,,AD-S82H	PL-000724-TS	ASSEMBLY,WAVEGUIDE W/FLARE PORT,90 X 60, 1",AD-S82H / I-82H,,,	Superseded
SP-000032-00	WAVEGUIDE,90 X 60,1" THROAT,HIPS,,AD-S82	PL-000723-TS	ASSEMBLY,HF HORN,W/GASKET,HPR152i,,,	Related
SP-000033-00	OBS-WOOFER,5",FIBERGLASS,FERRITE,AUDAX AP130FGS,	SP-000058-00	WOOFER,5",,,ZYLUX,AD-S52	Substitute
SP-000037-00	SOB-WOOFER,15",PAPER,FERRITE,EMINENCE 03-15-021,	SP-000104-00	WOOFER,15",PAPER,FERRITE,EMINENCE,WL115/CINEMA	Superseded
SP-000048-00	OBS-WOOFER,15",PAPER,FERRITE,B&C,15TBX40	SP-000074-00	SOB-WOOFER,(MD-L115,MD-S215)15",8 OHM,,B&C 15TBX100,	Substitute
SP-000051-00	OBS-COMPRESSION DRIVER,1", B&C, DE-200, 8ohm	SP-000111-00	DRIVER,1",COMPRESSION,,B&C DE-200, 8 OHM (AD-S282H)	Substitute
SP-000072-00	OBS-WOOFER,8",8/056-16 TWP,,B&C,	SP-000112-00	WOOFER,8",,,B&C 8/056-16 TWP,	Superseded
SP-000077-00	WOOFER,10",16 OHM,,B&C 10/110F-16,	SP-000195-00	WOOFER,10",,FERRITE,B&C,(WEATHERIZED)	Related
SP-000081-00	OBS-WOOFER,15",PAPER,FERRITE,CELESTION,FTR15-3070C	SP-000081-GP	WOOFER,15",PAPER,FERRITE,CELESTION,FTR-3070C-T5452_ GPE	Superseded
SP-000089-GP	SRV-WOOFER,10",,FERRITE,KSC,	SP-000152-GP	WOOFER,,,10",FERRITE,,KSC,SR110B THX	Superseded
SP-000090-GP	SRV-WOOFER,8",,FERRITE,KSC,	SP-000153-GP	WOOFER,,,8",FERRITE,,KSC,SR18 THX	Superseded
SP-000103-00	OBS-COMPRESSION DRIVER,1",CLA SERIES,TITANIUM,NEO,B&C DE400-TN8	SP-000113-00	DRIVER,1",COMPRESSION,NEO,B&C DE400-TN8,8.86 OHMS	Substitute
SP-000106-GP	OBS-HORN, HPR122i,,,,,	PL-000722-TS	ASSEMBLY,HF HORN,W/GASKET,HPR122i,,,	Superseded

Continued on next page ➜

Table 2. General QSC part updates

Original Part #	Description	New Part #	Description	Relationship
SP-000161-GP	TWEETER 4 OHM,3/4" INCH,,,,AD-S32T	PA-000172-GP	AD-S32T BAFFLE, INCLUDES TWEETER	Superseded
SR-000014-00	SRV - NL8 NEUTRIK CONNECTOR	CO-000339-00	CONN,NL8MPR,,,WL2082-i	Superseded
SR-000025-00	SRV - WOOFER GASKET	PS-000130-00	GASKET,1/8" THICK X 1/4" WIDE,CLOSED CELL FOAM,	Substitute
SR-000027-00	SRV - BACK PANEL GASKET	PS-000128-00	GASKET,1/8" THICK X 1/2" WIDE (50ft ROLL),CLOSED CELL FOAM,	Substitute
SR-000048-00	SRV - BACK PANEL (RIGHT), LINK BLOCK	CH-000456-01	BRACKET,PINNING, LEFT,BLACK, REAR RIGGING,WL2102-w,	Superseded
SR-000049-00	SRV - BACK PANEL (LEFT), LINK BLOCK	CH-000456-02	BRACKET,PINNING, RIGHT,BLACK, REAR RIGGING,WL2102-w,	Superseded
SR-000052-00	SRV - T-HANDLE BALL LOCKING PIN, 5/16"D x 0.75"L	HW-000126-00	PIN,RIGGING,SKY-PIN,5/16'D X 0.810"L, T HDL,5.5",LANYARD, CUSTOM,	Superseded
SR-000081-00	SRV - BUTTON-HANDLE BALL LOCKING PIN, 5/16x1.25	HW-000166-TS	BALL LOCK PIN,RND HD,5/16,1.125,17-4 SS,W/6.0"L,STL LANYARD	Superseded
SR-000092-00	DRIVER, 16 OHM, 1.4"COMPRESSION ,TITANIUM, NEO, B&C DE900TN-16	SP-000078-00	COMPRESSION DRIVER,,,,B&C DE900TN-16,	Substitute
SR-000123-00	PCB ASSY., DCM2, MONITOR BOARD ONLY (NO SURROUND)	SG-000050-00	PCB ASSY,PROCESSOR/SURROUND,DCM2,,SUB ASSY	Substitute
SR-000127-00	CABLE ASSY, 3 CONDUCTOR	WC-000434-TS	CABLE ASSY,,,3 COND,,,	Substitute
SW-000003-CB	SRV-CIRCUIT BREAKER,THERMAL,3A,	SW-000119-GP	CIRCUIT BREAKER,3A,230V, HPR,	Related
SW-000010-CB	CIRCUIT BREAKER,THERMAL,10A,	SW-000086-GP	CIRCUIT BRKR 10AMP	Substitute
SW-000015-CB	CIRCUIT BREAKER,THERMAL,15A,	SW-000091-GP	CIRCUIT BREAKER 15A	Substitute
SW-000016-SW	AC SWITCH,SPST,20A,125VAC,	SW-000088-GP	ROCKER POWER SWITCH	Substitute
SW-000029-SW	SRV-RELAY,SPDT,24VDC COIL,20A,125VAC,T90 STYLE	SW-000104-00	RELAY,SPDT,24VDC COIL,20A,125VAC,T90 STYLE (FOR PLC MODELS)	Substitute
SW-000053-00	SWITCH,SPST X 10,20 PIN DIP,PCB MOUNT LONG LEADS	SW-000089-GP	10 POLE DIP SWITCH	Substitute
SW-000128-TS	E.T.A. CIRCUIT BREAKER,,,	SW-0007.5-CB	SRV - 7.5A CIRCUIT BREAKER	Substitute
SW-000153-TS	CIRCUIT BREAKER 10A	SW-000086-GP	CIRCUIT BRKR 10AMP	Superseded
SW-000154-GP	OBS-CIRCUIT BREAKER,15A,,	SW-000091-GP	CIRCUIT BREAKER 15A	Superseded
SW-000155-GP	OBS-CIRCUIT BREAKER,8A,,	SW-000094-GP	CIRCUIT BREAKER 8A	Superseded
TD-000003-CD	SRV - TECHNICAL SUPPORT DVD	TD-000311-TS	DVD,,,TECH SUPPORT/QSC PRODUCT INFORMATION	Superseded
TD-000133-00	OBS-OWNERS MANUAL,BASIS,REPLACED BY RM-000007-00	RM-000007-00	CD,SCREENED,SLEEVED,BURNED,MULTI-LANGUAGE,OWNERS MANUAL,BASIS 922AZ,	Substitute
TD-000134-00	OBS-ACCESSORY OFFER SHEET,,NEW LOGO	TD-000047-00	OBS-ACCESSORY OFFER SHEET,,	Substitute
TD-000233-GP	QUICK START GUIDE,HPRi SERIES,PRINTED	RM-000008-GP	CD,OWNERS MANUAL,QUICK START GUIDE,,HPRi SERIES,	Superseded
TD-000234-00	SRV OBS-USER MANUAL,HPRi SERIES,PRINTED VERSION	RM-000008-GP	CD,OWNERS MANUAL,QUICK START GUIDE,,HPRi SERIES,	Superseded
TD-000241-GP	OBS-UL WARNING SHEET,,	TD-000241-00	CARTON INSERT,HPRi SAFETY SHEET,	Superseded
TD-001500-AX	SRV - MX SERVICE MANUAL	TD-001500-DL	SRV-SERVICE MANUAL,MX,DOWNLOADABLE VERSION	Superseded
WC-000015-WC	SRV - 14 LINE RIBBON	WC-000014-01	SRV-RIBBON CABLE ASSY,,28 AWG,14 CONDUCTOR,EX 2RU,10.3" L,	Substitute
WC-000103-00	RIBBON CABLE ASSY,,28 AWG,20 CONDUCTOR,PLC,9" L,	SG-000210-AC	SRV - PLC UPDATE KIT	Substitute
WC-000130-00	SRV-CABLE ASSY,POWER SUPPLY/AMP,24 AWG,8 CONDUCTOR,PL9.0,9.5" L,	WC-000243-00	SRV-CABLE ASSY,POWER SUPPLY TO AMP,24 AWG,8 CONDUCTOR,EVICTOR,12" L,	Substitute
WC-000181-GP	AC CORD 15A, 14 AWG, ISA/RMX	WC-000139-00	AC CORD,IEC,14 AWG,3 CONDUCTOR,PLC,72" L MINIMUM,125 VAC	Substitute
WC-000213-GP	AC CORD,HPR153F,230V	WC-000362-GP	POWER CORD,240V,IEC V-LOCK,0.75MM, 3M,,CEE 7/7,,	Superseded
WC-000213-GP	AC CORD,HPR153F,230V	WC-000054-00	AC CORD,,,3 CONDUCTOR,PLC,2.5 METERS,250 VAC	Substitute
WC-000421-GP	AC CORD SET,15A, 120v, HPRf	WC-000436-GP	SRV PH OUT-POWER CORD,IEC,18AWG,,HPRi,,120V 3M	Substitute
WC-000422-GP	OBS-POWER CORD SET,CE,,,,,	WC-000213-GP	AC CORD,HPR153F,230V	Superseded
WC-000436-GP	SRV PH OUT-POWER CORD,IEC,18AWG,,HPRi,,120V 3M	WC-000361-GP	POWER CORD,120V,IEC V-LOCK,18AWG, 3M,,NEMA 5-15,,	Substitute
WC-000438-GP	OBS-POWER CORD SET,CE,,,,,	WC-000348-GP	SRV-POWERCORD,IEC, CCC,18AWG,,HPRi,3M,	Superseded
WC-000456-00	WIRE HARNESS,,,,K8,,	WC-000458-00	WIRE HARNESS,,,,K12,,	Related
WC-000457-00	WIRE HARNESS,,,,K10,,	WC-000458-00	WIRE HARNESS,,,,K12,,	Related
WP-000057-00	FAN ASSY,,PLC,,	SG-000042-AC	SRV-PLC FAN UPGRADE	Substitute
WP-000058-00	SRV-BRACKET, REAR RAIL/RACK MOUNT ASSY,3" w/ HARDWARE	FG-000031-00	3" REAR SUPPORT RACK EAR KIT	Superseded
WP-000099-00	LOCKOUT PLATE ASSY,,CX/DCA,,4CH	WP-000083-00	SHIP KIT,,DCA,,4CH	Related
WP-000171-00	OBS-PCB ASSY,MAIN,PL9.0,,	WP-000182-00	OBS-PCB ASSY,,PL 9.0 (NEW),,	Substitute
WP-000261-00	OBS-PCB ASSY,MAIN,PL6.0,,	WP-000276-00	SRV-PCB ASSY,,PL 6.0II NON-PFC,,	Substitute
WP-000306-00	OBS-MAIN PCB ASSEMBLY,,ISA300T,,(RIGHT CHANNEL)	WP-000326-00	PCB ASSY,MAIN,ISA300TI,,BOTTOM	Superseded
WP-004012-00	SRV - OBS-EX4000 FAN ASSY	WP-004012-01	OBS-FAN ASSY,MX3000A,,	Substitute
WP-004051-00	OBS-PCB ASSY,,RMX4050HD,,	WP-004061-00	PCB ASSY,,RMX4050HD,,	Superseded
WP-004052-02	PCB ASSY,AC,RMX4050HD,230V,	WP-004052-00	PCB ASSY,AC,RMX4050HD,120V/240V,	Substitute
WP-004056-00	PCB ASSY,DISPLAY,RMX4050HD,,W/GAIN POTS	WP-005056-00	PCB ASSY,DISPLAY/GAIN CONTROL,RMX4050/RMX5050,,	Related
WP-004101-10	SRV - EX1250 MODULE ASSY	FG-004102-10	SRV - EX1250 CHANNEL MODULE	Substitute
WP-005051-00	PCB ASSY,,RMX5050,,	WP-005052-00	PCB ASSY,,RMX5050,,	Superseded

Continued on next page ➜

Table 2, continued. General QSC part updates

Original Part #	Description	New Part #	Description	Relationship
WP-018501-00	PCB ASSY,,RMX1850HD,,	WP-018503-00	PCB ASSY,PWR MOD,RT,RMX1850HD,,W/GAIN POTS	Superseded
WP-140002-CP	SRV - 1400 FAN	MS-000069-00	OBS-FAN,115VAC,OPEN FRAME,ASSY,	Substitute
WP-200001-TS	SRV-PCB ASSY,,GX3,100/120/240V,	WP-200001-00	PCB ASSY,,GX3,100/120/240V,	Superseded
WP-300001-TS	SRV-PCB ASSY,,GX5,100/120/240V,	WP-300001-00	PCB ASSY,,GX5,100/120/240V,	Superseded
XF-000050-00	SRV - XFMR, PWR, PLX3002	XF-000150-00	TRANSFORMER,SWITCHING,115KHZ,E55,1500W,DCA3022, 120V/230V,	Substitute
XF-000079-00	SRV - XFMR PLX 1202/2402	XF-000179-00	TRANSFORMER,SWITCHING,115KHZ,E55,1500W,DCA1222, 120V/230V,	Substitute
XF-000115-GP	TRANSFORMER (1806-2507+0), 120/230V,,,,,RMX 2450,,	XF-000319-GP	TRANSFORMER (1806-3986+0000),,,,120V,RMX2450,,	Related
XF-000115-GP	TRANSFORMER (1806-2507+0), 120/230V,,,,,RMX 2450,,	XF-000318-GP	TRANSFORMER,,,,(1806-3987+0000),240V,RMX2450,,	Related
XF-000312-TS	OBS-TRANSFORMER,I/P: 100/120/240,,,,,,	XF-000192-GP	TRANSFORMER,(1806-3542+1),120/240v, ISA800T/750	Superseded
XF-000325-GP	TRANSFORMER,(1806-3994+0000),240V,ISA450/500Ti,,	XF-000189-GP	TRANSFORMER,(1806-2422+0),120/240v, ISA450/500T	Substitute
XF-000326-GP	TRANSFORMER (1806-3993+0000),,,,120V,ISA450/500Ti,,	XF-000189-GP	TRANSFORMER,(1806-2422+0),120/240v, ISA450/500T	Substitute
XF-000601-00	TRANSFORMER,OUTPUT AUTOFORMER,,,600W,OT-600A,70V,	FG-000033-00	ACCESSORY,OT-600,,,	Substitute

Contact information

This bulletin is available for download from the Service Bulletins page in the *Tech Support* section of the QSC Audio Web site: **http://www.qscaudio.com/support/technical_support/bulletins.htm**. If you need any further information regarding this service procedure, please contact QSC Technical Services at the addresses or numbers below.

Telephone: 1-800-772-2834 (within USA only)
+1 (714) 957-7150

Fax: +1 (714) 754-6173

Skype: qscaudio

E-mail: tech_support@qscaudio.com

Web sites: www.qscaudio.com (product info/support)
www.qscparts.com (on-line accessory and replacement component sales)

Postal and parcel address: **QSC Audio Products, LLC**
Technical Services Group
1665 MacArthur Blvd.
Costa Mesa, CA 92626 USA